

TEST

TEST 9 BIC,BIC,BIT  
MD-11-DOI-A

EP-DOI-A-DL-A  
COPYRIGHT © 1976  
FICHE 1 OF 1

NOV 1976  
digital  
MADE IN USA

Microfiche grid containing multiple frames of data.

100









# GO1

MAC11: 27.732' 01-007-76 10:26 PAGE 8

0011.P11  
0011  
0011  
0011

EQUALITY. ALL CONDITIONAL BRANCHES THAT WILL  
BEHAVE ON ANY FORM OF EQUALITY ARE ALSO TESTED.  
BOTH WORD AND BYTE OPERATIONS ARE USED.

(9 CONT'D)

TEST 7 COMPARE NOT, THIS IS A TEST OF THE COMPARE INSTRUCTIONS WHERE NO VALLES ARE EQUAL. WE DE BRANCHES FOR NOT EQUAL, GREATER THAN AND LESS THAN, ETC., ARE TESTED.

TEST 8 CHECKS THE MOVE INSTRUCTION BOTH TO MEMORY AND REGISTERS.

TEST 9 CHECK THE BIS, BIC AND BIT INSTRUCTION BOTH TO MEMORY AND TO REGISTERS.

TEST 10 TESTS THE ADD INSTRUCTION.

TEST 11 TESTS THE SUBTRACT INSTRUCTION.

TEST 12 TEST OF THE JUMP INSTRUCTION IN MOST MODES.

NOTE THAT STACK OPERATION AND INSTRUCTIONS THAT USE THEM ARE NOT TESTED IN THIS GROUP OF TEST.

- 10. LISTING
- 11. FLOW CHART(S)

MACY11 27.732) 01-OCT-76 10:26 PAGE 9







J01

MAIN MACY11 27.732) 01-OCT-76 10:26 PAGE 11  
CCIA.P11

137  
138  
139



Vertical text on the left side of the page, appearing to be a list of identifiers or a column of data, possibly related to the test cases.

177775 000002  
000002 177775  
177773 000004  
000004 177773  
177767 000010  
000010 177767  
177757 000020  
000020 177757  
177737 000040  
000040 177737  
177677 000100  
000100 177677

0177775.02  
02.0177775  
0177773.04  
04.0177773  
0177767.010  
010.0177767  
0177757.020  
020.0177757  
0177737.040  
040.0177737  
0177677.0100  
0100.0177677

: SHOULD NOT SET Z  
:BIT 177775 2 FAILED TO SET Z  
: SHOULD NOT SET Z  
:BIT 2 177775 FAILED TO SET Z  
: SHOULD NOT SET Z  
:BIT 177773 4 FAILED TO SET Z  
: SHOULD NOT SET Z  
:BIT 4 177773 FAILED TO SET Z  
: SHOULD NOT SET Z  
:BIT 177767 10 FAILED TO SET Z  
: SHOULD NOT SET Z  
:BIT 10 177767 FAILED TO SET Z  
: SHOULD NOT SET Z  
:BIT 177757 20 FAILED TO SET Z  
: SHOULD NOT SET Z  
:BIT 20 177757 FAILED TO SET Z  
: SHOULD NOT SET Z  
:BIT 177737 40 FAILED TO SET Z  
: SHOULD NOT SET Z  
:BIT 40 177737 FAILED TO SET Z  
: SHOULD NOT SET Z  
:BIT 177677 100 FAILED TO SET Z  
: SHOULD NOT SET Z





# NO1

478	001042	000000				HLT			;BIT 167777 10000 FAILED TO SET Z
479	001044	000240				SCOPE			
480	001046	032727	010000	167777		BIT	#10000,#167777		;SHOULD NOT SET Z
481	001054	001401				BEQ	.+4		
482	001056	000000				HLT			;BIT 10000 167777 FAILED TO SET Z
483		020000				N=N+N			
484		157777				M=M+M+1			
485	001060	000240				SCOPE			
486	001062	032727	157777	020000		BIT	#157777.#20000		;SHOULD NOT SET Z
487	001070	001401				BEQ	.+4		
488	001072	000000				HLT			;BIT 157777 20000 FAILED TO SET Z
489	001074	000240				SCOPE			
490	001076	032727	020000	157777		BIT	#20000,#157777		;SHOULD NOT SET Z
491	001104	001401				BEQ	.+4		
492	001106	000000				HLT			;BIT 20000 157777 FAILED TO SET Z
493		040000				N=N+N			
494		137777				M=M+M+1			
495	001110	000240				SCOPE			
496	001112	032727	137777	040000		BIT	#137777,#40000		;SHOULD NOT SET Z
497	001120	001401				BEQ	.+4		
498	001122	000000				HLT			;BIT 137777 40000 FAILED TO SET Z
499	001124	000240				SCOPE			
500	001126	032727	040000	137777		BIT	#40000,#137777		;SHOULD NOT SET Z
501	001134	001401				BEQ	.+4		
502	001136	000000				HLT			;BIT 40000 137777 FAILED TO SET Z
503		100000				N=N+N			
504		077777				M=M+M+1			
505									
506									
507	001140	000240				SCOPE			;TEST FOR NOT EQUAL WORD AND BYTE
508	001142	032727	177777	177777		BIT	#177777,#177777		;SHOULD NOT SET Z
509	001150	001001				BNE	.+4		
510	001152	000000				HLT			;FALSE SET OF Z
511	001154	000240				SCOPE			
512	001156	032727	177400	177777		BIT	#177400,#177777		;SHOULD NOT SET Z
513	001164	001001				BNE	.+4		
514	001166	000000				HLT			;FALSE SET OF Z
515	001170	000240				SCOPE			
516	001172	032727	000377	177777		BIT	#377,#-1		;SHOULD NOT SET Z
517	001200	001001				BNE	.+4		
518	001202	000000				HLT			;FALSE SET OF Z
519	001204	000240				SCOPE			
520	001206	032727	177777	177400		BIT	#-1,#177400		;SHOULD NOT SET Z
521	001214	001001				BNE	.+4		
522	001216	000000				HLT			;FALSE SET OF Z
523	001220	000240				SCOPE			
524	001222	032727	177777	000377		BIT	#-1,#377		;SHOULD NOT SET Z
525	001230	001001				BNE	.+4		
526	001232	000000				HLT			;FALSE SET OF Z
527	001234	000240				SCOPE			
528	001236	132727	177777	177777		BITB	#-1,#-1		;SHOULD NOT SET Z
529	001244	001001				BNE	.+4		
530	001246	000000				HLT			;FALSE SET OF Z
531	001250	000240				SCOPE			
532	001252	132727	000377	177777		BITB	#377,#-1		;SHOULD NOT SET Z
533	001260	001001				BNE	.+4		

DATA. P11  
MAY 11 27.732 01-OCT-76 10:26 PAGE 16

MINIMUM  
MAXIMUM  
MINIMUM  
MAXIMUM  
MINIMUM  
MAXIMUM  
MINIMUM  
MAXIMUM

000000  
000000  
000000  
000000  
000000  
000000  
000000  
000000

000000  
000000  
000000  
000000  
000000  
000000  
000000  
000000

177777 000377

MINIMUM  
MAXIMUM  
MINIMUM  
MAXIMUM  
MINIMUM  
MAXIMUM  
MINIMUM  
MAXIMUM

0-1,8377  
.4

:FALSE SET OF Z  
:SHOULD NOT SET Z  
:FALSE SET OF Z



541	001300	000240			SCOPE		
542	001302	032727	000001	177777	BIT #1, #-1		; SHOULD NOT SET Z
543	001310	001001			BNE .+4		
544	001312	000000			HLT		; FALSE SET OF Z
545	001314	000240			SCOPE		
546	001316	032727	177777	000001	BIT #-1, #1		; SHOULD NOT SET Z
547	001324	001001			SNE .+4		
548	001326	000000			HLT		; FALSE SET OF Z
549		000002			N=N+N		
550	001330	000240			SCOPE		
551	001332	032727	000002	177777	BIT #2, #-1		; SHOULD NOT SET Z
552	001340	001001			SNE .+4		
553	001342	000000			HLT		; FALSE SET OF Z
554	001344	000240			SCOPE		
555	001346	032727	177777	000002	BIT #-1, #2		; SHOULD NOT SET Z
556	001354	001001			BNE .+4		
557	001356	000000			HLT		; FALSE SET OF Z
558		000004			N=N+N		
559	001360	000240			SCOPE		
560	001362	032727	000004	177777	BIT #4, #-1		; SHOULD NOT SET Z
561	001370	001001			BNE .+4		
562	001372	000000			HLT		; FALSE SET OF Z
563	001374	000240			SCOPE		
564	001376	032727	177777	000004	BIT #-1, #4		; SHOULD NOT SET Z
565	001404	001001			BNE .+4		
566	001406	000000			HLT		; FALSE SET OF Z
567		000010			N=N+N		
568	001410	000240			SCOPE		
569	001412	032727	000010	177777	BIT #10, #-1		; SHOULD NOT SET Z
570	001420	001001			BNE .+4		
571	001422	000000			HLT		; FALSE SET OF Z
572	001424	000240			SCOPE		
573	001426	032727	177777	000010	BIT #-1, #10		; SHOULD NOT SET Z
574	001434	001001			BNE .+4		
575	001436	000000			HLT		; FALSE SET OF Z
576		000020			N=N+N		
577	001440	000240			SCOPE		
578	001442	032727	000020	177777	BIT #20, #-1		; SHOULD NOT SET Z
579	001450	001001			BNE .+4		
580	001452	000000			HLT		; FALSE SET OF Z
581	001454	000240			SCOPE		
582	001456	032727	177777	000020	BIT #-1, #20		; SHOULD NOT SET Z
583	001464	001001			BNE .+4		
584	001466	000000			HLT		; FALSE SET OF Z
585		000040			N=N+N		
586	001470	000240			SCOPE		
587	001472	032727	000040	177777	BIT #40, #-1		; SHOULD NOT SET Z
588	001500	001001			BNE .+4		
589	001502	000000			HLT		; FALSE SET OF Z
590	001504	000240			SCOPE		
591	001506	032727	177777	000040	BIT #-1, #40		; SHOULD NOT SET Z
592	001514	001001			BNE .+4		
593	001516	000000			HLT		; FALSE SET OF Z
594		000100			N=N+N		
595	001520	000240			SCOPE		
596	001522	032727	000100	177777	BIT #100, #-1		; SHOULD NOT SET Z

597	001530	001001			BNE	.+4	
598	001532	000000			HLT		;FALSE SET OF Z
599	001534	000240			SCOPE		
600	001536	032727	177777	000100	BIT	#-1,#100	;SHOULD NOT SET Z
601	001544	001001			BNE	.+4	
602	001546	000000			HLT		;FALSE SET OF Z
603		000200			N=N+N		
604	001550	000240			SCOPE		
605	001552	032727	000200	177777	BIT	#200,#-1	;SHOULD NOT SET Z
606	001550	001001			BNE	.+4	
607	001562	000000			HLT		;FALSE SET OF Z
608	001564	000240			SCOPE		
609	001566	032727	177777	000200	BIT	#-1,#200	;SHOULD NOT SET Z
610	001574	001001			BNE	.+4	
611	001576	000000			HLT		;FALSE SET OF Z
612		000400			N=N+N		
613	001600	000240			SCOPE		
614	001602	032727	000400	177777	BIT	#400,#-1	;SHOULD NOT SET Z
615	001610	001001			BNE	.+4	
616	001612	000000			HLT		;FALSE SET OF Z
617	001614	000240			SCOPE		
618	001616	032727	177777	000400	BIT	#-1,#400	;SHOULD NOT SET Z
619	001624	001001			BNE	.+4	
620	001626	000000			HLT		;FALSE SET OF Z
621		001000			N=N+N		
622	001630	000240			SCOPE		
623	001632	032727	001000	177777	BIT	#1000,#-1	;SHOULD NOT SET Z
624	001640	001001			BNE	.+4	
625	001642	000000			HLT		;FALSE SET OF Z
626	001644	000240			SCOPE		
627	001646	032727	177777	001000	BIT	#-1,#1000	;SHOULD NOT SET Z
628	001654	001001			BNE	.+4	
629	001656	000000			HLT		;FALSE SET OF Z
630		002000			N=N+N		
631	001660	000240			SCOPE		
632	001662	032727	002000	177777	BIT	#2000,#-1	;SHOULD NOT SET Z
633	001670	001001			BNE	.+4	
634	001672	000000			HLT		;FALSE SET OF Z
635	001674	000240			SCOPE		
636	001676	032727	177777	002000	BIT	#-1,#2000	;SHOULD NOT SET Z
637	001704	001001			BNE	.+4	
638	001706	000000			HLT		;FALSE SET OF Z
639		004000			N=N+N		
640	001710	000240			SCOPE		
641	001712	032727	004000	177777	BIT	#4000,#-1	;SHOULD NOT SET Z
642	001720	001001			BNE	.+4	
643	001722	000000			HLT		;FALSE SET OF Z
644	001724	000240			SCOPE		
645	001726	032727	177777	004000	BIT	#-1,#4000	;SHOULD NOT SET Z
646	001734	001001			BNE	.+4	
647	001736	000000			HLT		;FALSE SET OF Z
648		010000			N=N+N		
649	001740	000240			SCOPE		
650	001742	032727	010000	177777	BIT	#10000,#-1	;SHOULD NOT SET Z
651	001750	001001			BNE	.+4	
652	001752	000000			HLT		;FALSE SET OF Z

653	001754	000240			SCOPE		
654	001756	032727	177777	010000	BIT	#-1, #10000	; SHOULD NOT SET Z
655	001764	001001			BNE	.+4	
656	001766	000000			HLT		; FALSE SET OF Z
657		020000			N=N+N		
658	001770	000240			SCOPE		
659	001772	032727	020000	177777	BIT	#20000, #-1	; SHOULD NOT SET Z
660	002000	001001			BNE	.+4	
661	002002	000000			HLT		; FALSE SET OF Z
662	002004	000240			SCOPE		
663	002006	032727	177777	020000	BIT	#-1, #20000	; SHOULD NOT SET Z
664	002014	001001			BNE	.+4	
665	002016	000000			HLT		; FALSE SET OF Z
666		040000			N=N+N		
667	002020	000240			SCOPE		
668	002022	032727	040000	177777	BIT	#40000, #-1	; SHOULD NOT SET Z
669	002030	001001			BNE	.+4	
670	002032	000000			HLT		; FALSE SET OF Z
671	002034	000240			SCOPE		
672	002036	032727	177777	040000	BIT	#-1, #40000	; SHOULD NOT SET Z
673	002044	001001			BNE	.+4	
674	002046	000000			HLT		; FALSE SET OF Z
675		100000			N=N+N		
676	002050	000240			SCOPE		
677	002052	032727	100000	177777	BIT	#100000, #-1	; SHOULD NOT SET Z
678	002060	001001			BNE	.+4	
679	002062	000000			HLT		; FALSE SET OF Z
680	002064	000240			SCOPE		
681	002066	032727	177777	100000	BIT	#-1, #100000	; SHOULD NOT SET Z
682	002074	001001			BNE	.+4	
683	002076	000000			HLT		; FALSE SET OF Z
684		000000			N=N+N		
685							
686		000000			N=0		
687	002100	000240			SCOPE		
688	002102	012700	177777		MOV	#-1, %N	
689	002106	032700	000000		BIT	#0, %N	; SHOULD SET Z
690	002112	001401			BEQ	.+4	
691	002114	000000			HLT		; BIT FAILED TO SET Z
692	002116	000240			SCOPE		
693	002120	012700	000000		MOV	#0, %N	
694	002124	032700	177777		BIT	#-1, %N	; SHOULD SET Z
695	002130	001401			BEQ	.+4	
696	002132	000000			HLT		; BIT FAILED TO SET Z
697		000001			N=N+1		
698	002134	000240			SCOPE		
699	002136	012701	177777		MOV	#-1, %N	
700	002142	032701	000000		BIT	#0, %N	; SHOULD SET Z
701	002146	001401			BEQ	.+4	
702	002150	000000			HLT		; BIT FAILED TO SET Z
703	002152	000240			SCOPE		
704	002154	012701	000000		MOV	#0, %N	
705	002160	032701	177777		BIT	#-1, %N	; SHOULD SET Z
706	002164	001401			BEQ	.+4	
707	002166	000000			HLT		; BIT FAILED TO SET Z
708		000002			N=N+1		

709	002170	000240		SCOPE	
710	002172	012702	177777	MOV #0,%N	
711	002176	032702	000000	BIT #0,%N	;SHOULD SET Z
712	002202	001401		BEQ .+4	
713	002204	000000		HLT	;BIT FAILED TO SET Z
714	002206	000240		SCOPE	
715	002210	012702	000000	MOV #0,%N	
716	002214	032702	177777	BIT #-1,%N	;SHOULD SET Z
717	002220	001401		BEQ .+4	
718	002222	000000		HLT	;BIT FAILED TO SET Z
719		000003		N=N+1	
720	002224	000240		SCOPE	
721	002226	012703	177777	MOV #0,%N	
722	002232	032703	000000	BIT #0,%N	;SHOULD SET Z
723	002236	001401		BEQ .+4	
724	002240	000000		HLT	;BIT FAILED TO SET Z
725	002242	000240		SCOPE	
726	002244	012703	000000	MOV #0,%N	
727	002250	032703	177777	BIT #-1,%N	;SHOULD SET Z
728	002254	001401		BEQ .+4	
729	002256	000000		HLT	;BIT FAILED TO SET Z
730		000004		N=N+1	
731	002260	000240		SCOPE	
732	002262	012704	177777	MOV #0,%N	
733	002266	032704	000000	BIT #0,%N	;SHOULD SET Z
734	002272	001401		BEQ .+4	
735	002274	000000		HLT	;BIT FAILED TO SET Z
736	002276	000240		SCOPE	
737	002300	012704	000000	MOV #0,%N	
738	002304	032704	177777	BIT #-1,%N	;SHOULD SET Z
739	002310	001401		BEQ .+4	
740	002312	000000		HLT	;BIT FAILED TO SET Z
741		000005		N=N+1	
742	002314	000240		SCOPE	
743	002316	012705	177777	MOV #0,%N	
744	002322	032705	000000	BIT #0,%N	;SHOULD SET Z
745	002326	001401		BEQ .+4	
746	002330	000000		HLT	;BIT FAILED TO SET Z
747	002332	000240		SCOPE	
748	002334	012705	000000	MOV #0,%N	
749	002340	032705	177777	BIT #-1,%N	;SHOULD SET Z
750	002344	001401		BEQ .+4	
751	002346	000000		HLT	;BIT FAILED TO SET Z
752		000006		N=N+1	
753					
754		000001		N=1	
755		177776		M=177776	
756	002350	000240		SCOPE	
757	002352	012700	000001	MOV #1,RO	
758	002356	032700	177776	BIT #177776,RO	;SHOULD SET Z
759	002362	001401		BEQ .+4	
760	002364	000000		HLT	;BIT FAILED TO SET Z
761	002366	000240		SCOPE	
762	002370	012700	177776	MOV #177776,RO	
763	002374	032700	000001	BIT #1,RO	;SHOULD SET Z
764	002400	001401		BEQ .+4	

765	002402	000000			HLT		;BIT FAILED TO SET Z
766	002404	000240			SCOPE		
767	002406	012767	000001	011536	MOV	#1,TEMP	
768	002414	032767	177776	011530	BIT	#177776,TEMP	; SHOULD SET Z
769	002422	001401			BEQ	.+4	
770	002424	000000			HLT		;BIT FAILED TO SET Z
771	002426	000240			SCOPE		
772	002430	012767	177776	011514	MOV	#177776,TEMP	
773	002436	032767	000001	011506	BIT	#1,TEMP	; SHOULD SET Z
774	002444	001401			BEQ	.+4	
775	002446	000000			HLT		;BIT FAILED TO SET Z
776		000002			N=N+N		
777		177775			M=M+M+1		
778	002450	000240			SCOPE		
779	002452	012700	000002		MOV	#2,RO	
780	002456	032700	177775		BIT	#177775,RO	; SHOULD SET Z
781	002462	001401			BEQ	.+4	
782	002464	000000			HLT		;BIT FAILED TO SET Z
783	002466	000240			SCOPE		
784	002470	012700	177775		MOV	#177775,RO	
785	002474	032700	000002		BIT	#2,RO	; SHOULD SET Z
786	002500	001401			BEQ	.+4	
787	002502	000000			HLT		;BIT FAILED TO SET Z
788	002504	000240			SCOPE		
789	002506	012767	000002	011436	MOV	#2,TEMP	
790	002514	032767	177775	011430	BIT	#177775,TEMP	; SHOULD SET Z
791	002522	001401			BEQ	.+4	
792	002524	000000			HLT		;BIT FAILED TO SET Z
793	002526	000240			SCOPE		
794	002530	012767	177775	011414	MOV	#177775,TEMP	
795	002536	032767	000002	011406	BIT	#2,TEMP	; SHOULD SET Z
796	002544	001401			BEQ	.+4	
797	002546	000000			HLT		;BIT FAILED TO SET Z
798		000004			N=N+N		
799		177773			M=M+M+1		
800	002550	000240			SCOPE		
801	002552	012700	000004		MOV	#4,RO	
802	002556	032700	177773		BIT	#177773,RO	; SHOULD SET Z
803	002562	001401			BEQ	.+4	
804	002564	000000			HLT		;BIT FAILED TO SET Z
805	002566	000240			SCOPE		
806	002570	012700	177773		MOV	#177773,RO	
807	002574	032700	000004		BIT	#4,RO	; SHOULD SET Z
808	002600	001401			BEQ	.+4	
809	002602	000000			HLT		;BIT FAILED TO SET Z
810	002604	000240			SCOPE		
811	002606	012767	000004	011336	MOV	#4,TEMP	
812	002614	032767	177773	011330	BIT	#177773,TEMP	; SHOULD SET Z
813	002622	001401			BEQ	.+4	
814	002624	000000			HLT		;BIT FAILED TO SET Z
815	002626	000240			SCOPE		
816	002630	012767	177773	011314	MOV	#177773,TEMP	
817	002636	032767	000004	011306	BIT	#4,TEMP	; SHOULD SET Z
818	002644	001401			BEQ	.+4	
819	002646	000000			HLT		;BIT FAILED TO SET Z
820		000010			N=N+N		

# H02

822	002650	177767				M=M+M+1			
823	002652	012700	000010			SCOPE			
824	002656	032700	177767			MOV #10,RO			
825	002662	001401				BIT #177767,RO			; SHOULD SET Z
826	002664	000000				BEQ .+4			
827	002666	000240				HLT			; BIT FAILED TO SET Z
828	002670	012700	177767			SCOPE			
829	002674	032700	000010			MOV #177767,RO			
830	002700	001401				BIT #10,RO			; SHOULD SET Z
831	002702	000000				BEQ .+4			
832	002704	000240				HLT			; BIT FAILED TO SET Z
833	002706	012767	000010	011236		SCOPE			
834	002714	032767	177767	011230		MOV #10,TEMP			
835	002722	001401				BIT #177767,TEMP			; SHOULD SET Z
836	002724	000000				BEQ .+4			
837	002726	000240				HLT			; BIT FAILED TO SET Z
838	002730	012767	177767	011214		SCOPE			
839	002736	032767	000010	011206		MOV #177767,TEMP			
840	002744	001401				BIT #10,TEMP			; SHOULD SET Z
841	002746	000000				BEQ .+4			
842		000020				HLT			; BIT FAILED TO SET Z
843		177757				N=N+N			
844	002750	000240				M=M+M+1			
845	002752	012700	000020			SCOPE			
846	002756	032700	177757			MOV #20,RO			
847	002762	001401				BIT #177757,RO			; SHOULD SET Z
848	002764	000000				BEQ .+4			
849	002766	000240				HLT			; BIT FAILED TO SET Z
850	002770	012700	177757			SCOPE			
851	002774	032700	000020			MOV #177757,RO			
852	003000	001401				BIT #20,RO			; SHOULD SET Z
853	003002	000000				BEQ .+4			
854	003004	000240				HLT			; BIT FAILED TO SET Z
855	003006	012767	000020	011136		SCOPE			
856	003014	032767	177757	011130		MOV #20,TEMP			
857	003022	001401				BIT #177757,TEMP			; SHOULD SET Z
858	003024	000000				BEQ .+4			
859	003026	000240				HLT			; BIT FAILED TO SET Z
860	003030	012767	177757	011114		SCOPE			
861	003036	032767	000020	011106		MOV #177757,TEMP			
862	003044	001401				BIT #20,TEMP			; SHOULD SET Z
863	003046	000000				BEQ .+4			
864		000040				HLT			; BIT FAILED TO SET Z
865		177737				N=N+N			
866	003050	000240				M=M+M+1			
867	003052	012700	000040			SCOPE			
868	003056	032700	177737			MOV #40,RO			
869	003062	001401				BIT #177737,RO			; SHOULD SET Z
870	003064	000000				BEQ .+4			
871	003066	000240				HLT			; BIT FAILED TO SET Z
872	003070	012700	177737			SCOPE			
873	003074	032700	000040			MOV #177737,RO			
874	003100	001401				BIT #40,RO			; SHOULD SET Z
875	003102	000000				BEQ .+4			
876	003104	000240				HLT			; BIT FAILED TO SET Z
						SCOPE			

877	003106	012767	000040	011036	MOV	#40,TEMP		
878	003114	032767	177737	011030	BIT	#177737,TEMP		; SHOULD SET Z
879	003122	001401			BEQ	.+4		
880	003124	000000			HLT			; BIT FAILED TO SET Z
881	003126	000240			SCOPE			
882	003130	012767	177737	011014	MOV	#177737,TEMP		
883	003136	032767	000040	011006	BIT	#40,TEMP		; SHOULD SET Z
884	003144	001401			BEQ	.+4		
885	003146	000000			HLT			; BIT FAILED TO SET Z
886		000100			N=N+N			
887		177677			M=M+M+1			
888	003150	000240			SCOPE			
889	003152	012700	000100		MOV	#100,RO		
890	003156	032700	177677		BIT	#177677,RO		; SHOULD SET Z
891	003162	001401			BEQ	.+4		
892	003164	000000			HLT			; BIT FAILED TO SET Z
893	003166	000240			SCOPE			
894	003170	012700	177677		MOV	#177677,RO		
895	003174	032700	000100		BIT	#100,RO		; SHOULD SET Z
896	003200	001401			BEQ	.+4		
897	003202	000000			HLT			; BIT FAILED TO SET Z
898	003204	000240			SCOPE			
899	003206	012767	000100	010736	MOV	#100,TEMP		
900	003214	032767	177677	010730	BIT	#177677,TEMP		; SHOULD SET Z
901	003222	001401			BEQ	.+4		
902	003224	000000			HLT			; BIT FAILED TO SET Z
903	003226	000240			SCOPE			
904	003230	012767	177677	010714	MOV	#177677,TEMP		
905	003236	032767	000100	010706	BIT	#100,TEMP		; SHOULD SET Z
906	003244	001401			BEQ	.+4		
907	003246	000000			HLT			; BIT FAILED TO SET Z
908		000200			N=N+N			
909		177577			M=M+M+1			
910	003250	000240			SCOPE			
911	003252	012700	000200		MOV	#200,RO		
912	003256	032700	177577		BIT	#177577,RO		; SHOULD SET Z
913	003262	001401			BEQ	.+4		
914	003264	000000			HLT			; BIT FAILED TO SET Z
915	003266	000240			SCOPE			
916	003270	012700	177577		MOV	#177577,RO		
917	003274	032700	000200		BIT	#200,RO		; SHOULD SET Z
918	003300	001401			BEQ	.+4		
919	003302	000000			HLT			; BIT FAILED TO SET Z
920	003304	000240			SCOPE			
921	003306	012767	000200	010636	MOV	#200,TEMP		
922	003314	032767	177577	010630	BIT	#177577,TEMP		; SHOULD SET Z
923	003322	001401			BEQ	.+4		
924	003324	000000			HLT			; BIT FAILED TO SET Z
925	003326	000240			SCOPE			
926	003330	012767	177577	010614	MOV	#177577,TEMP		
927	003336	032767	000200	010606	BIT	#200,TEMP		; SHOULD SET Z
928	003344	001401			BEQ	.+4		
929	003346	000000			HLT			; BIT FAILED TO SET Z
930		000400			N=N+N			
931		177377			M=M+M+1			
932	003350	000240			SCOPE			



933	003352	012700	000400		MOV	#400,RO		
934	003356	032700	177377		BIT	#177377,RO		; SHOULD SET Z
935	003362	001401			BEQ	.+4		
936	003364	000000			HLT			; BIT FAILED TO SET Z
937	003266	000240			SCOPE			
938	003370	012700	177377		MOV	#177377,RO		
939	003374	032700	000400		BIT	#400,RO		; SHOULD SET Z
940	003400	001401			BEQ	.+4		
941	003402	000000			HLT			; BIT FAILED TO SET Z
942	003404	000240			SCOPE			
943	003406	012767	000400	010536	MOV	#400,TEMP		
944	003414	032767	177377	010530	BIT	#177377,TEMP		; SHOULD SET Z
945	003422	001401			BEQ	.+4		
946	003424	000000			HLT			; BIT FAILED TO SET Z
947	003426	000240			SCOPE			
948	003430	012767	177377	010514	MOV	#177377,TEMP		
949	003436	032767	000400	010506	BIT	#400,TEMP		; SHOULD SET Z
950	003444	001401			BEQ	.+4		
951	003446	000000			HLT			; BIT FAILED TO SET Z
952		001000			N=N+N			
953		176777			M=M+M+1			
954	003450	000240			SCOPE			
955	003452	012700	001000		MOV	#1000,RO		
956	003456	032700	176777		BIT	#176777,RO		; SHOULD SET Z
957	003462	001401			BEQ	.+4		
958	003464	000000			HLT			; BIT FAILED TO SET Z
959	003466	000240			SCOPE			
960	003470	012700	176777		MOV	#176777,RO		
961	003474	032700	001000		BIT	#1000,RO		; SHOULD SET Z
962	003500	001401			BEQ	.+4		
963	003502	000000			HLT			; BIT FAILED TO SET Z
964	003504	000240			SCOPE			
965	003506	012767	001000	010436	MOV	#1000,TEMP		
966	003514	032767	176777	010430	BIT	#176777,TEMP		; SHOULD SET Z
967	003522	001401			BEQ	.+4		
968	003524	000000			HLT			; BIT FAILED TO SET Z
969	003526	000240			SCOPE			
970	003530	012767	176777	010414	MOV	#176777,TEMP		
971	003536	032767	001000	010406	BIT	#1000,TEMP		; SHOULD SET Z
972	003544	001401			BEQ	.+4		
973	003546	000000			HLT			; BIT FAILED TO SET Z
974		002000			N=N+N			
975		175777			M=M+M+1			
976	003550	000240			SCOPE			
977	003552	012700	002000		MOV	#2000,RO		
978	003556	032700	175777		BIT	#175777,RO		; SHOULD SET Z
979	003562	001401			BEQ	.+4		
980	003564	000000			HLT			; BIT FAILED TO SET Z
981	003566	000240			SCOPE			
982	003570	012700	175777		MOV	#175777,RO		
983	003574	032700	002000		BIT	#2000,RO		; SHOULD SET Z
984	003600	001401			BEQ	.+4		
985	003602	000000			HLT			; BIT FAILED TO SET Z
986	003604	000240			SCOPE			
987	003606	012767	002000	010336	MOV	#2000,TEMP		
988	003614	032767	175777	010330	BIT	#175777,TEMP		; SHOULD SET Z

# K02

.MAIN. MACY11 27(732) 01-OCT-75 10:26 PAGE 25  
 DOJIA.P11

989	003622	001401			BEQ	.+4	
990	003624	000000			HLT		;BIT FAILED TO SET Z
991	003626	000240			SCOPE		
992	003630	012767	175777	010314	MOV	#175777,TEMP	
993	003636	032767	0C2000	010306	BIT	#2000,TEMP	;SHOULD SET Z
994	003644	001401			BEQ	.+4	
995	003646	000000			HLT		;BIT FAILED TO SET Z
996		004000			N=N+N		
997		173777			M=M+M+1		
998	003650	000240			SCOPE		
999	003652	012700	004000		MOV	#4000,RO	
1000	003656	032700	173777		BIT	#173777,RO	;SHOULD SET Z
1001	003662	001401			BEQ	.+4	
1002	003664	000000			HLT		;BIT FAILED TO SET Z
1003	003666	000240			SCOPE		
1004	003670	012700	173777		MOV	#173777,RO	
1005	003674	032700	004000		BIT	#4000,RO	;SHOULD SET Z
1006	003700	001401			BEQ	.+4	
1007	003702	000000			HLT		;BIT FAILED TO SET Z
1008	003704	000240			SCOPE		
1009	003706	012767	004000	010236	MOV	#4000,TEMP	
1010	003714	032767	173777	010230	BIT	#173777,TEMP	;SHOULD SET Z
1011	003722	001401			BEQ	.+4	
1012	003724	000000			HLT		;BIT FAILED TO SET Z
1013	003726	000240			SCOPE		
1014	003730	012767	173777	010214	MOV	#173777,TEMP	
1015	003736	032767	004000	010206	BIT	#4000,TEMP	;SHOULD SET Z
1016	003744	001401			BEQ	.+4	
1017	003746	000000			HLT		;BIT FAILED TO SET Z
1018		010000			N=N+N		
1019		167777			M=M+M+1		
1020	003750	000240			SCOPE		
1021	003752	012700	010000		MOV	#10000,RO	
1022	003756	032700	167777		BIT	#167777,RO	;SHOULD SET Z
1023	003762	001401			BEQ	.+4	
1024	003764	000000			HLT		;BIT FAILED TO SET Z
1025	003766	000240			SCOPE		
1026	003770	012700	167777		MOV	#167777,RO	
1027	003774	032700	010000		BIT	#10000,RO	;SHOULD SET Z
1028	004000	001401			BEQ	.+4	
1029	004002	000000			HLT		;BIT FAILED TO SET Z
1030	004004	000240			SCOPE		
1031	004006	012767	010000	010136	MOV	#10000,TEMP	
1032	004014	032767	167777	010130	BIT	#167777,TEMP	;SHOULD SET Z
1033	004022	001401			BEQ	.+4	
1034	004024	0C0000			HLT		;BIT FAILED TO SET Z
1035	004026	000240			SCOPE		
1036	004030	012767	167777	010114	MOV	#167777,TEMP	
1037	004036	032767	010000	010106	BIT	#10000,TEMP	;SHOULD SET Z
1038	004044	001401			BEQ	.+4	
1039	004046	000000			HLT		;BIT FAILED TO SET Z
1040		020000			N=N+N		
1041		157777			M=M+M+1		
1042	004050	000240			SCOPE		
1043	004052	012700	020000		MOV	#20000,RO	
1044	004056	032700	157777		BIT	#157777,RO	;SHOULD SET Z

1045	004062	001401			BEQ	.+4	
1046	004064	000000			HLT		;BIT FAILED TO SET Z
1047	004066	000240			SCOPE		
1049	004070	012700	157777		MOV	#157777,RO	
1049	004074	032700	020000		BIT	#20000,RO	;SHOULD SET Z
1050	004100	001401			BEQ	.+4	
1051	004102	000000			HLT		;BIT FAILED TO SET Z
1052	004104	000240			SCOPE		
1053	004106	012767	020000	010036	MOV	#20000,TEMP	
1054	004114	032767	157777	010030	BIT	#157777,TEMP	;SHOULD SET Z
1055	004122	001401			BEQ	.+4	
1056	004124	000000			HLT		;BIT FAILED TO SET Z
1057	004126	000240			SCOPE		
1058	004130	012767	157777	010014	MOV	#157777,TEMP	
1059	004136	032767	020000	010006	BIT	#20000,TEMP	;SHOULD SET Z
1060	004144	001401			BEQ	.+4	
1061	004146	000000			HLT		;BIT FAILED TO SET Z
1062		040000			N=N+N		
1063		137777			M=M+M+1		
1064	004150	000240			SCOPE		
1065	004152	012700	040000		MOV	#40000,RO	
1066	004156	032700	137777		BIT	#137777,RO	;SHOULD SET Z
1067	004162	001401			BEQ	.+4	
1068	004164	000000			HLT		;BIT FAILED TO SET Z
1069	004166	000240			SCOPE		
1070	004170	012700	137777		MOV	#137777,RO	
1071	004174	032700	040000		BIT	#40000,RO	;SHOULD SET Z
1072	004200	001401			BEQ	.+4	
1073	004202	000000			HLT		;BIT FAILED TO SET Z
1074	004204	000240			SCOPE		
1075	004206	012767	040000	007736	MOV	#40000,TEMP	
1076	004214	032767	137777	007730	BIT	#137777,TEMP	;SHOULD SET Z
1077	004222	001401			BEQ	.+4	
1078	004224	000000			HLT		;BIT FAILED TO SET Z
1079	004226	000240			SCOPE		
1080	004230	012767	137777	007714	MOV	#137777,TEMP	
1081	004236	032767	040000	007706	BIT	#40000,TEMP	;SHOULD SET Z
1082	004244	001401			BEQ	.+4	
1083	004246	000000			HLT		;BIT FAILED TO SET Z
1084		100000			N=N+N		
1085		077777			M=M+M+1		
1086	004250	000240			SCOPE		
1087	004252	012700	100000		MOV	#100000,RO	
1088	004256	032700	077777		BIT	#77777,RO	;SHOULD SET Z
1089	004262	001401			BEQ	.+4	
1090	004264	000000			HLT		;BIT FAILED TO SET Z
1091	004266	000240			SCOPE		
1092	004270	012700	077777		MOV	#77777,RO	
1093	004274	032700	100000		BIT	#100000,RO	;SHOULD SET Z
1094	004300	001401			BEQ	.+4	
1095	004302	000000			HLT		;BIT FAILED TO SET Z
1096	004304	000240			SCOPE		
1097	004306	012767	100000	007636	MOV	#100000,TEMP	
1098	004314	032767	077777	007630	BIT	#77777,TEMP	;SHOULD SET Z
1099	004322	001401			BEQ	.+4	
1100	004324	000000			HLT		;BIT FAILED TO SET Z

M02

1101	004326	000240		SCOPE	
1102	004330	012767	077777 007614	MOV	#77777,TEMP ; SHOULD SET Z
1103	004336	032767	100000 007606	BIT	#100000,TEMP
1104	004344	001401		BEQ	.+4
1105	004346	000000		HLT	;BIT FAILED TO SET Z
1106		000000		N=N+N	
1107		177777		M=M+M+1	
1108	004350	000240		SCOPE	
1109	004352	012767	000377 007572	MOV	#377,TEMP ; SHOULD SET Z
1110	004360	132767	000000 007564	BITB	#0,TEMP
1111	004366	001401		BEQ	.+4
1112	004370	000000		HLT	;BITB FAILED TO SET Z
1113	004372	000240		SCOPE	
1114	004374	012767	177400 007550	MOV	#177400,TEMP ; SHOULD SET Z
1115	004402	132767	000000 007542	BITB	#0,TEMP
1116	004410	001401		BEQ	.+4
1117	004412	000000		HLT	;BITB FAILED TO SET Z
1118					
1119		000000		M=0	
1120	004414	000240		SCOPE	
1121	004416	012700	177777	MOV	#-1,%N ; SHOULD NOT SET Z
1122	004422	032700	177777	BIT	#-1,%N
1123	004426	001001		BNE	.+4
1124	004430	000000		HLT	;BIT -1,%N SET Z
1125	004432	000240		SCOPE	
1126	004434	012700	177400	MOV	#177400,%N ; SHOULD NOT SET Z
1127	004440	032700	177777	BIT	#-1,%N
1128	004444	001001		BNE	.+4
1129	004446	000000		HLT	;BIT -1,%N SET Z
1130	004450	000240		SCOPE	
1131	004452	012700	000377	MOV	#377,%N ; SHOULD NOT SET Z
1132	004456	032700	177777	BIT	#-1,%N
1133	004462	001001		BNE	.+4
1134	004464	000000		HLT	;BIT -1,%N SET Z
1135	004466	000240		SCOPE	
1136	004470	012700	177777	MOV	#-1,%N ; SHOULD NOT SET Z
1137	004474	032700	177400	BIT	#177400,%N
1138	004500	001001		BNE	.+4
1139	004502	000000		HLT	;BIT 177400,%N SET Z
1140	004504	000240		SCOPE	
1141	004506	012700	177777	MOV	#-1,%N ; SHOULD NOT SET Z
1142	004512	032700	000377	BIT	#377,%N
1143	004516	001001		BNE	.+4
1144	004520	000000		HLT	;BIT 377,%N SET Z
1145	004522	000240		SCOPE	
1146	004524	012700	177777	MOV	#-1,%N ; SHOULD NOT SET Z
1147	004530	132700	177777	BITB	#-1,%N
1148	004534	001001		BNE	.+4
1149	004536	000000		HLT	;BITB -1,%N SET Z
1150	004540	000240		SCOPE	
1151	004542	012700	000377	MOV	#377,%N ; SHOULD NOT SET Z
1152	004546	132700	177777	BITB	#-1,%N
1153	004552	001001		BNE	.+4
1154	004554	000000		HLT	;BITB -1,%N SET Z
1155		000001		M=M+1	
1156	004556	000240		SCOPE	

1157	004560	012700	177777	MOV	#-1,%N	
1158	004564	032700	177777	BIT	#-1,%N	;SHOULD NOT SET Z
1159	004570	001001		BNE	.+4	
1160	004572	000000		HLT		;BIT -1,%N SET Z
1161	004574	000240		SCOPE		
1162	004576	012700	177400	MOV	#177400,%N	
1163	004602	032700	177777	BIT	#-1,%N	;SHOULD NOT SET Z
1164	004606	001001		BNE	.+4	
1165	004610	000000		HLT		;BIT -1,%N SET Z
1166	004612	000240		SCOPE		
1167	004614	012700	000377	MOV	#377,%N	
1168	004620	032700	177777	BIT	#-1,%N	;SHOULD NOT SET Z
1169	004624	001001		BNE	.+4	
1170	004626	000000		HLT		;BIT -1,%N SET Z
1171	004630	000240		SCOPE		
1172	004632	012700	177777	MOV	#-1,%N	
1173	004636	032700	177400	BIT	#177400,%N	;SHOULD NOT SET Z
1174	004642	001001		BNE	.+4	
1175	004644	000000		HLT		;BIT 177400,%N SET Z
1176	004646	000240		SCOPE		
1177	004650	012700	177777	MOV	#-1,%N	
1178	004654	032700	000377	BIT	#377,%N	;SHOULD NOT SET Z
1179	004660	001001		BNE	.+4	
1180	004662	000000		HLT		;BIT 377,%N SET Z
1181	004664	000240		SCOPE		
1182	004666	012700	177777	MOV	#-1,%N	
1183	004672	132700	177777	BITB	#-1,%N	;SHOULD NOT SET Z
1184	004676	001001		BNE	.+4	
1185	004700	000000		HLT		;BITB -1,%N SET Z
1186	004702	000240		SCOPE		
1187	004704	012700	000377	MOV	#377,%N	
1188	004710	132700	177777	BITB	#-1,%N	;SHOULD NOT SET Z
1189	004714	001001		BNE	.+4	
1190	004716	000000		HLT		;BITB -1,%N SET Z
1191		000002		M=M+1		
1192	004720	000240		SCOPE		
1193	004722	012700	177777	MOV	#-1,%N	
1194	004726	032700	177777	BIT	#-1,%N	;SHOULD NOT SET Z
1195	004732	001001		BNE	.+4	
1196	004734	000000		HLT		;BIT -1,%N SET Z
1197	004736	000240		SCOPE		
1198	004740	012700	177400	MOV	#177400,%N	
1199	004744	032700	177777	BIT	#-1,%N	;SHOULD NOT SET Z
1200	004750	001001		BNE	.+4	
1201	004752	000000		HLT		;BIT -1,%N SET Z
1202	004754	000240		SCOPE		
1203	004756	012700	000377	MOV	#377,%N	
1204	004762	032700	177777	BIT	#-1,%N	;SHOULD NOT SET Z
1205	004766	001001		BNE	.+4	
1206	004770	000000		HLT		;BIT -1,%N SET Z
1207	004772	000240		SCOPE		
1208	004774	012700	177777	MOV	#-1,%N	
1209	005000	032700	177400	BIT	#177400,%N	;SHOULD NOT SET Z
1210	005004	001001		BNE	.+4	
1211	005006	000000		HLT		;BIT 177400,%N SET Z
1212	005010	000240		SCOPE		

1213	005012	012700	177777	MOV	#-1,%N	
1214	005016	032700	000377	BIT	#377,%N	;SHOULD NOT SET Z
1215	005022	001001		BNE	.+4	
1216	005024	000000		HLT		
1217	005026	000240		SCOPE		;BIT 377,%N SET Z
1218	005030	012700	177777	MOV	#-1,%N	
1219	005034	132700	177777	BITB	#-1,%N	;SHOULD NOT SET Z
1220	005040	001001		BNE	.+4	
1221	005042	000000		HLT		
1222	005044	000240		SCOPE		;BITB -1,%N SET Z
1223	005046	012700	000377	MOV	#377,%N	
1224	005052	132700	177777	BITB	#-1,%N	;SHOULD NOT SET Z
1225	005056	001001		BNE	.+4	
1226	005060	000000		HLT		
1227		000003		M=M+1		
1228	005062	000240		SCOPE		
1229	005064	012700	177777	MOV	#-1,%N	
1230	005070	032700	177777	EIT	#-1,%N	;SHOULD NOT SET Z
1231	005074	001001		BNE	.+4	
1232	005076	000000		HLT		
1233	005100	000240		SCOPE		;BIT -1,%N SET Z
1234	005102	012700	177400	MOV	#177400,%N	
1235	005106	032700	177777	BIT	#-1,%N	;SHOULD NOT SET Z
1236	005112	001001		BNE	.+4	
1237	005114	000000		HLT		;BIT -1,%N SET Z
1238	005116	000240		SCOPE		
1239	005120	012700	000377	MOV	#377,%N	
1240	005124	032700	177777	BIT	#-1,%N	;SHOULD NOT SET Z
1241	005130	001001		BNE	.+4	
1242	005132	000000		HLT		;BIT -1,%N SET Z
1243	005134	000240		SCOPE		
1244	005136	012700	177777	MOV	#-1,%N	
1245	005142	032700	177400	BIT	#177400,%N	;SHOULD NOT SET Z
1246	005146	001001		BNE	.+4	
1247	005150	000000		HLT		;BIT 177400,%N SET Z
1248	005152	000240		SCOPE		
1249	005154	012700	177777	MOV	#-1,%N	
1250	005160	032700	000377	BIT	#377,%N	;SHOULD NOT SET Z
1251	005164	001001		BNE	.+4	
1252	005166	000000		HLT		;BIT 377,%N SET Z
1253	005170	000240		SCOPE		
1254	005172	012700	177777	MOV	#-1,%N	
1255	005176	132700	177777	BITB	#-1,%N	;SHOULD NOT SET Z
1256	005202	001001		BNE	.+4	
1257	005204	000000		HLT		;BITB -1,%N SET Z
1258	005206	000240		SCOPE		
1259	005210	012700	000377	MOV	#377,%N	
1260	005214	132700	177777	BITB	#-1,%N	;SHOULD NOT SET Z
1261	005220	001001		BNE	.+4	
1262	005222	000000		HLT		;BITB -1,%N SET Z
1263		000004		M=M+1		
1264	005224	000240		SCOPE		
1265	005226	012700	177777	MOV	#-1,%N	
1266	005232	032700	177777	BIT	#-1,%N	;SHOULD NOT SET Z
1267	005236	001001		BNE	.+4	
1268	005240	000000		HLT		;BIT -1,%N SET Z

1269	005242	000240		SCOPE		
1270	005244	012700	177400	MOV	#177400,%N	
1271	005250	032700	177777	BIT	#-1,%N	; SHOULD NOT SET Z
1272	005254	001001		BNE	.+4	
1273	005256	000000		HLT		;BIT -1,%N SET Z
1274	005260	000240		SCOPE		
1275	005262	012700	000377	MOV	#377,%N	
1276	005266	032700	177777	BIT	#-1,%N	; SHOULD NOT SET Z
1277	005272	001001		BNE	.+4	
1278	005274	000000		HLT		;BIT -1,%N SET Z
1279	005276	000240		SCOPE		
1280	005300	012700	177777	MOV	#-1,%N	
1281	005304	032700	17.400	BIT	#177400,%N	; SHOULD NOT SET Z
1282	005310	001001		BNE	.+4	
1283	005312	000000		HLT		;BIT 177400,%N SET Z
1284	005314	000240		SCOPE		
1285	005316	012700	177777	MOV	#-1,%N	
1286	005322	032700	000377	BIT	#377,%N	; SHOULD NOT SET Z
1287	005326	001001		BNE	.+4	
1288	005330	000000		HLT		;BIT 377,%N SET Z
1289	005332	000240		SCOPE		
1290	005334	012700	177777	MOV	#-1,%N	
1291	005340	132700	177777	BITB	#-1,%N	; SHOULD NOT SET Z
1292	005344	001001		BNE	.+4	
1293	005346	000000		HLT		;BITB -1,%N SET Z
1294	005350	000240		SCOPE		
1295	005352	012700	000377	MOV	#377,%N	
1296	005356	132700	177777	BITB	#-1,%N	; SHOULD NOT SET Z
1297	005362	001001		BNE	.+4	
1298	005364	000000		HLT		;BITB -1,%N SET Z
1299		000005		M=M+1		
1300	005366	000240		SCOPE		
1301	005370	012700	177777	MOV	#-1,%N	
1302	005374	032700	177777	BIT	#-1,%N	; SHOULD NOT SET Z
1303	005400	001001		BNE	.+4	
1304	005402	000000		HLT		;BIT -1,%N SET Z
1305	005404	000240		SCOPE		
1306	005406	012700	177400	MOV	#177400,%N	
1307	005412	032700	177777	BIT	#-1,%N	; SHOULD NOT SET Z
1308	005416	001001		BNE	.+4	
1309	005420	000000		HLT		;BIT -1,%N SET Z
1310	005422	000240		SCOPE		
1311	005424	012700	000377	MOV	#377,%N	
1312	005430	032700	177777	BIT	#-1,%N	; SHOULD NOT SET Z
1313	005434	001001		BNE	.+4	
1314	005436	000000		HLT		;BIT -1,%N SET Z
1315	005440	000240		SCOPE		
1316	005442	012700	177777	MOV	#-1,%N	
1317	005446	032700	177400	BIT	#177400,%N	; SHOULD NOT SET Z
1318	005452	001001		BNE	.+4	
1319	005454	000000		HLT		;BIT 177400,%N SET Z
1320	005456	000240		SCOPE		
1321	005460	012700	177777	MOV	#-1,%N	
1322	005464	032700	000377	BIT	#377,%N	; SHOULD NOT SET Z
1323	005470	001001		BNE	.+4	
1324	005472	000000		HLT		;BIT 377,%N SET Z



1325	005474	000240		SCOPE		
1326	005476	012700	177777	MOV	#-1,%N	
1327	005502	132700	177777	BITB	#-1,%N	; SHOULD NOT SET Z
1329	005506	001001		BNE	.+4	
1329	005510	000000		HLT		; BITB -1,%N SET Z
1330	005512	000240		SCOPE		
1331	005514	012700	000377	MOV	#377,%N	
1332	005520	132700	177777	BITB	#-1,%N	; SHOULD NOT SET Z
1333	005524	001001		BNE	.+4	
1334	005526	000000		HLT		; BITB -1,%N SET Z
1335		000006		M=M+1		
1336						
1337	005530	000240		SCOPE		
1338	005532	012767	177777 006412	MOV	#-1,TEMP	
1339	005540	032767	177777 006404	BIT	#-1,TEMP	; SHOULD NOT SET Z
1340	005546	001001		BNE	.+4	
1341	005550	000000		HLT		; BIT -1,TEMP SET Z
1342	005552	000240		SCOPE		
1343	005554	012767	177777 006370	MOV	#-1,TEMP	
1344	005562	132767	177777 006362	BITB	#-1,TEMP	; SHOULD NOT SET Z
1345	005570	001001		BNE	.+4	
1346	005572	000000		HLT		; BITB -1,TEMP SET Z
1347	005574	000240		SCOPE		
1348	005576	012767	177777 006346	MOV	#-1,TEMP	
1349	005604	132767	000001 006340	BITB	#1,TEMP	; SHOULD NOT SET Z
1350	005612	001001		BNE	.+4	
1351	005614	000000		HLT		; BITB 1,TEMP SET Z
1352						
1353		000000		N=0		
1354	005616	012700	177777	MOV	#177777,%N	; MOV 177777 TO %N
1355	005622	042700	000000	BIC	#0,%N	; SELECTIVELY CLEAR %N
1356	005626	022700	177777	CMP	#-0-13177777,%N	; COMPARE LITERAL TO %N
1357	005632	001401		BEQ	.+4	; TEST FOR EQUAL
1358	005634	000000		HLT		; BIC INSTRUCTION FAILED
1359	005636	000240		SCOPE		
1360	005640	012700	177777	MOV	#177777,%N	; MOV 177777 TO %N
1361	005644	052700	000000	BIS	#0,%N	; SELECTIVE SET %N
1362	005650	022700	177777	CMP	#177777!0,%N	; COMPARE LITERAL TO %N
1363	005654	001401		BEQ	.+4	; TEST FOR EQUAL
1364	005656	000000		HLT		; BIS INSTRUCTION FAILED
1365	005660	000240		SCOPE		
1366	005662	012700	000000	MOV	#0,%N	; MOV 0 TO %N
1367	005666	042700	177777	BIC	#177777,%N	; SELECTIVELY CLEAR %N
1368	005672	022700	000000	CMP	#-177777-1&0,%N	; COMPARE LITERAL TO %N
1369	005676	001401		BEQ	.+4	; TEST FOR EQUAL
1370	005700	000000		HLT		; BIC INSTRUCTION FAILED
1371	005702	000240		SCOPE		
1372	005704	012700	000000	MOV	#0,%N	; MOV 0 TO %N
1373	005710	052700	177777	BIS	#177777,%N	; SELECTIVE SET %N
1374	005714	022700	177777	CMP	#0!177777,%N	; COMPARE LITERAL TO %N
1375	005720	001401		BEQ	.+4	; TEST FOR EQUAL
1376	005722	000000		HLT		; BIS INSTRUCTION FAILED
1377	005724	000240		SCOPE		
1378		000001		N=N+1		
1379	005726	012701	177777	MOV	#177777,%N	; MOV 177777 TO %N
1380	005732	042701	000000	BIC	#0,%N	; SELECTIVELY CLEAR %N

# E03

1381	005736	022701	177777	CMP	#-0-1&177777,%N	;COMPARE LITERAL TO %N
1382	005742	001401		BEQ	.+4	;TEST FOR EQUAL
1383	005744	000000		HLT		;BIC INSTRUCTION FAILED
1384	005746	000240		SCOPE		
1385	005750	012701	177777	MOV	#177777,%N	;MOV 177777 TO %N
1386	005754	052701	000000	BIS	#0,%N	;SELECTIVE SET %N
1387	005760	022701	177777	CMP	#177777!0,%N	;COMPARE LITERAL TO %N
1388	005764	001401		BEQ	.+4	;TEST FOR EQUAL
1389	005766	000000		HLT		;BIS INSTRUCTION FAILED
1390	005770	000240		SCOPE		
1391	005772	012701	000000	MOV	#0,%N	;MOV 0 TO %N
1392	005776	042701	177777	BIC	#177777,%N	;SELECTIVELY CLEAR %N
1393	006002	022701	000000	CMP	#-177777-1&0,%N	;COMPARE LITERAL TO %N
1394	006006	001401		BEQ	.+4	;TEST FOR EQUAL
1395	006010	000000		HLT		;BIC INSTRUCTION FAILED
1396	006012	000240		SCOPE		
1397	006014	012701	000000	MOV	#0,%N	;MOV 0 TO %N
1398	006020	052701	177777	BIS	#177777,%N	;SELECTIVE SET %N
1399	006024	022701	177777	CMP	#0!177777,%N	;COMPARE LITERAL TO %N
1400	006030	001401		BEQ	.+4	;TEST FOR EQUAL
1401	006032	000000		HLT		;BIS INSTRUCTION FAILED
1402	006034	000240		SCOPE		
1403		000002		N=N+1		
1404	006036	012702	177777	MOV	#177777,%N	;MOV 177777 TO %N
1405	006042	042702	000000	BIC	#0,%N	;SELECTIVELY CLEAR %N
1406	006046	022702	177777	CMP	#-0-1&177777,%N	;COMPARE LITERAL TO %N
1407	006052	001401		BEQ	.+4	;TEST FOR EQUAL
1408	006054	000000		HLT		;BIC INSTRUCTION FAILED
1409	006056	000240		SCOPE		
1410	006060	012702	177777	MOV	#177777,%N	;MOV 177777 TO %N
1411	006064	052702	000000	BIS	#0,%N	;SELECTIVE SET %N
1412	006070	022702	177777	CMP	#177777!0,%N	;COMPARE LITERAL TO %N
1413	006074	001401		BEQ	.+4	;TEST FOR EQUAL
1414	006076	000000		HLT		;BIS INSTRUCTION FAILED
1415	006100	000240		SCOPE		
1416	006102	012702	000000	MOV	#0,%N	;MOV 0 TO %N
1417	006106	042702	177777	BIC	#177777,%N	;SELECTIVELY CLEAR %N
1418	006112	022702	000000	CMP	#-177777-1&0,%N	;COMPARE LITERAL TO %N
1419	006116	001401		BEQ	.+4	;TEST FOR EQUAL
1420	006120	000000		HLT		;BIC INSTRUCTION FAILED
1421	006122	000240		SCOPE		
1422	006124	012702	000000	MOV	#0,%N	;MOV 0 TO %N
1423	006130	052702	177777	BIS	#177777,%N	;SELECTIVE SET %N
1424	006134	022702	177777	CMP	#0!177777,%N	;COMPARE LITERAL TO %N
1425	006140	001401		BEQ	.+4	;TEST FOR EQUAL
1426	006142	000000		HLT		;BIS INSTRUCTION FAILED
1427	006144	000240		SCOPE		
1428		000003		N=N+1		
1429	006146	012703	177777	MOV	#177777,%N	;MOV 177777 TO %N
1430	006152	042703	000000	BIC	#0,%N	;SELECTIVELY CLEAR %N
1431	006156	022703	177777	CMP	#-0-1&177777,%N	;COMPARE LITERAL TO %N
1432	006162	001401		BEQ	.+4	;TEST FOR EQUAL
1433	006164	000000		HLT		;BIC INSTRUCTION FAILED
1434	006166	000240		SCOPE		
1435	006170	012703	177777	MOV	#177777,%N	;MOV 177777 TO %N
1436	006174	052703	000000	BIS	#0,%N	;SELECTIVE SET %N

# F03

.MAIN. MACY11 27.732) 01-OCT-76 10:26 PAGE 33  
 DOIA.P11

1437	006200	022703	177777	CMP	#177777!0,%N	;COMPARE LITERAL TO %N
1438	006204	001401		BEQ	.+4	;TEST FOR EQUAL
1439	006206	000000		HLT		;BIS INSTRUCTION FAILED
1440	006210	000240		SCOPE		
1441	006212	012703	000000	MOV	#0,%N	;MOV 0 TO %N
1442	006216	042703	177777	BIC	#177777,%N	;SELECTIVELY CLEAR %N
1443	006222	022703	000000	CMP	#-177777-1&0,%N	;COMPARE LITERAL TO %N
1444	006226	001401		BEQ	.+4	;TEST FOR EQUAL
1445	006230	000000		HLT		;BIC INSTRUCTION FAILED
1446	006232	000240		SCOPE		
1447	006234	012703	000000	MOV	#0,%N	;MOV 0 TO %N
1448	006240	052703	177777	BIS	#177777,%N	;SELECTIVE SET %N
1449	006244	022703	177777	CMP	#0!177777,%N	;COMPARE LITERAL TO %N
1450	006250	001401		BEQ	.+4	;TEST FOR EQUAL
1451	006252	000000		HLT		;BIS INSTRUCTION FAILED
1452	006254	000240		SCOPE		
1453		000004		N=N+1		
1454	006256	012704	177777	MOV	#177777,%N	;MOV 177777 TO %N
1455	006262	042704	000000	BIC	#0,%N	;SELECTIVELY CLEAR %N
1456	006266	022704	177777	CMP	#-0-1&177777,%N	;COMPARE LITERAL TO %N
1457	006272	001401		BEQ	.+4	;TEST FOR EQUAL
1458	006274	000000		HLT		;BIC INSTRUCTION FAILED
1459	006276	000240		SCOPE		
1460	006300	012704	177777	MOV	#177777,%N	;MOV 177777 TO %N
1461	006304	052704	000000	BIS	#0,%N	;SELECTIVE SET %N
1462	006310	022704	177777	CMP	#177777!0,%N	;COMPARE LITERAL TO %N
1463	006314	001401		BEQ	.+4	;TEST FOR EQUAL
1464	006316	000000		HLT		;BIS INSTRUCTION FAILED
1465	006320	000240		SCOPE		
1466	006322	012704	000000	MOV	#0,%N	;MOV 0 TO %N
1467	006326	042704	177777	BIC	#177777,%N	;SELECTIVELY CLEAR %N
1468	006332	022704	000000	CMP	#-177777-1&0,%N	;COMPARE LITERAL TO %N
1469	006336	001401		BEQ	.+4	;TEST FOR EQUAL
1470	006340	000000		HLT		;BIC INSTRUCTION FAILED
1471	006342	000240		SCOPE		
1472	006344	012704	000000	MOV	#0,%N	;MOV 0 TO %N
1473	006350	052704	177777	BIS	#177777,%N	;SELECTIVE SET %N
1474	006354	022704	177777	CMP	#0!177777,%N	;COMPARE LITERAL TO %N
1475	006360	001401		BEQ	.+4	;TEST FOR EQUAL
1476	006362	000000		HLT		;BIS INSTRUCTION FAILED
1477	006364	000240		SCOPE		
1478		000005		N=N+1		
1479	006366	012705	177777	MOV	#177777,%N	;MOV 177777 TO %N
1480	006372	042705	000000	BIC	#0,%N	;SELECTIVELY CLEAR %N
1481	006376	022705	177777	CMP	#-0-1&177777,%N	;COMPARE LITERAL TO %N
1482	006402	001401		BEQ	.+4	;TEST FOR EQUAL
1483	006404	000000		HLT		;BIC INSTRUCTION FAILED
1484	006406	000240		SCOPE		
1485	006410	012705	177777	MOV	#177777,%N	;MOV 177777 TO %N
1486	006414	052705	000000	BIS	#0,%N	;SELECTIVE SET %N
1487	006420	022705	177777	CMP	#177777!0,%N	;COMPARE LITERAL TO %N
1488	006424	001401		BEQ	.+4	;TEST FOR EQUAL
1489	006426	000000		HLT		;BIS INSTRUCTION FAILED
1490	006430	000240		SCOPE		
1491	006432	012705	000000	MOV	#0,%N	;MOV 0 TO %N
1492	006436	042705	177777	BIC	#177777,%N	;SELECTIVELY CLEAR %N

1493	006442	022705	000000			CMP	#-177777-1&0,%N	;COMPARE LITERAL TO %N
1494	006446	001401				BEQ	.+4	;TEST FOR EQUAL
1495	006450	000000				HLT		;BIC INSTRUCTION FAILED
1496	006452	000240				SCOPE		
1497	006454	012705	000000			MOV	#0,%N	;MOV 0 TO %N
1498	006460	052705	177777			BIS	#177777,%N	;SELECTIVE SET %N
1499	006464	022705	177777			CMP	#0!177777,%N	;COMPARE LITERAL TO %N
1500	006470	001401				BEQ	.+4	;TEST FOR EQUAL
1501	006472	000000				HLT		;BIS INSTRUCTION FAILED
1502	006474	000240				SCOPE		
1503		000006				N=N+1		
1504								
1505		000001				N=1		
1506		177776				M=177776		
1507	006476	012700	000001			MOV	#1,RO	;MOV 1 TO RO
1508	006502	042700	177776			BIC	#177776,RO	;SELECTIVELY CLEAR RO
1509	006506	022700	000001			CMP	#-177776-1&1,RO	;COMPARE LITERAL TO RO
1510	006512	001401				BEQ	.+4	;TEST FOR EQUAL
1511	006514	000000				HLT		;BIC INSTRUCTION FAILED
1512	006516	000240				SCOPE		
1513	006520	012700	000001			MOV	#1,RO	;MOV 1 TO RO
1514	006524	052700	177776			BIS	#177776,RO	;SELECTIVE SET RO
1515	006530	022700	177777			CMP	#1!177776,RO	;COMPARE LITERAL TO RO
1516	006534	001401				BEQ	.+4	;TEST FOR EQUAL
1517	006536	000000				HLT		;BIS INSTRUCTION FAILED
1518	006540	000240				SCOPE		
1519	006542	012700	177776			MOV	#177776,RO	;MOV 177776 TO RO
1520	006546	042700	000001			BIC	#1,RO	;SELECTIVELY CLEAR RO
1521	006552	022700	177776			CMP	#-1-1&177776,RO	;COMPARE LITERAL TO RO
1522	006556	001401				BEQ	.+4	;TEST FOR EQUAL
1523	006560	000000				HLT		;BIC INSTRUCTION FAILED
1524	006562	000240				SCOPE		
1525	006564	012700	177776			MOV	#177776,RO	;MOV 177776 TO RO
1526	006570	052700	000001			BIS	#1,RO	;SELECTIVE SET RO
1527	006574	022700	177777			CMP	#177776!1,RO	;COMPARE LITERAL TO RO
1528	006600	001401				BEQ	.+4	;TEST FOR EQUAL
1529	006602	000000				HLT		;BIS INSTRUCTION FAILED
1530	006604	000240				SCOPE		
1531	006606	012767	000001	005336		MOV	#1,TEMP	;MOV 1 TO TEMP
1532	006614	042767	177776	005330		BIC	#177776,TEMP	;SELECTIVELY CLEAR TEMP
1533	006622	022767	000001	005322		CMP	#-177776-1&1,TEMP	;COMPARE LITERAL TO TEMP
1534	006630	001401				BEQ	.	;TEST FOR EQUAL
1535	006632	000000				HLT		;BIC INSTRUCTION FAILED
1536	006634	000240				SCOPE		
1537	006636	012767	000001	005306		MOV	#1,TEMP	;MOV 1 TO TEMP
1538	006644	052767	177776	005300		BIS	#177776,TEMP	;SELECTIVE SET TEMP
1539	006652	022767	177777	005272		CMP	#1!177776,TEMP	;COMPARE LITERAL TO TEMP
1540	006660	001401				BEQ	.+4	;TEST FOR EQUAL
1541	006662	000000				HLT		;BIS INSTRUCTION FAILED
1542	006664	000240				SCOPE		
1543	006666	012767	177776	005256		MOV	#177776,TEMP	;MOV 177776 TO TEMP
1544	006674	042767	000001	005250		BIC	#1,TEMP	;SELECTIVELY CLEAR TEMP
1545	006702	022767	177776	005242		CMP	#-1-1&177776,TEMP	;COMPARE LITERAL TO TEMP
1546	006710	001401				BEQ	.+4	;TEST FOR EQUAL
1547	006712	000000				HLT		;BIC INSTRUCTION FAILED
1548	006714	000240				SCOPE		

# H03

1549	006716	012767	177776	005226	MOV	#177775,TEMP	;MOV 177776 TO TEMP
1550	006724	052767	000001	005220	BIS	#1,TEMP	;SELECTIVE SET TEMP
1551	006732	022767	177777	005212	CMP	#177776!1,TEMP	;COMPARE LITERAL TO TEMP
1552	006740	001401			BEQ	.+4	;TEST FOR EQUAL
1553	006742	000000			HLT		;BIS INSTRUCTION FAILED
1554	006744	000240			SCOPE		
1555		000002			N=N+N		
1556		177775			M=M+M+1		
1557	006746	012700	000002		MOV	#2,RO	;MOV 2 TO RO
1558	006752	042700	177775		BIC	#177775,RO	;SELECTIVELY CLEAR RO
1559	006756	022700	000002		CMP	#-177775-1&2,RO	;COMPARE LITERAL TO RO
1560	006762	001401			BEQ	.+4	;TEST FOR EQUAL
1561	006764	000000			HLT		;BIC INSTRUCTION FAILED
1562	006766	000240			SCOPE		
1563	006770	012700	000002		MOV	#2,RO	;MOV 2 TO RO
1564	006774	052700	177775		BIS	#177775,RO	;SELECTIVE SET RO
1565	007000	022700	177777		CMP	#2!177775,RO	;COMPARE LITERAL TO RO
1566	007004	001401			BEQ	.+4	;TEST FOR EQUAL
1567	007006	000000			HLT		;BIS INSTRUCTION FAILED
1568	007010	000240			SCOPE		
1569	007012	012700	177775		MOV	#177775,RO	;MOV 177775 TO RO
1570	007016	042700	000002		BIC	#2,RO	;SELECTIVELY CLEAR RO
1571	007022	022700	177775		CMP	#-2-1&177775,RO	;COMPARE LITERAL TO RO
1572	007026	001401			BEQ	.+4	;TEST FOR EQUAL
1573	007030	000000			HLT		;BIC INSTRUCTION FAILED
1574	007032	000240			SCOPE		
1575	007034	012700	177775		MOV	#177775,RO	;MOV 177775 TO RO
1576	007040	052700	000002		BIS	#2,RO	;SELECTIVE SET RO
1577	007044	022700	177777		CMP	#177775!2,RO	;COMPARE LITERAL TO RO
1578	007050	001401			BEQ	.+4	;TEST FOR EQUAL
1579	007052	000000			HLT		;BIS INSTRUCTION FAILED
1580	007054	000240			SCOPE		
1581	007056	012767	000002	005066	MOV	#2,TEMP	;MOV 2 TO TEMP
1582	007064	042767	177775	005060	BIC	#177775,TEMP	;SELECTIVELY CLEAR TEMP
1583	007072	022767	000002	005052	CMP	#-177775-1&2,TEMP	;COMPARE LITERAL TO TEMP
1584	007100	001401			BEQ	.+4	;TEST FOR EQUAL
1585	007102	000000			HLT		;BIC INSTRUCTION FAILED
1586	007104	000240			SCOPE		
1587	007106	012767	000002	005036	MOV	#2,TEMP	;MOV 2 TO TEMP
1588	007114	052767	177775	005030	BIS	#177775,TEMP	;SELECTIVE SET TEMP
1589	007122	022767	177777	005022	CMP	#2!177775,TEMP	;COMPARE LITERAL TO TEMP
1590	007130	001401			BEQ	.+4	;TEST FOR EQUAL
1591	007132	000000			HLT		;BIS INSTRUCTION FAILED
1592	007134	000240			SCOPE		
1593	007136	012767	177775	005006	MOV	#177775,TEMP	;MOV 177775 TO TEMP
1594	007144	042767	000002	005000	BIC	#2,TEMP	;SELECTIVELY CLEAR TEMP
1595	007152	022767	177775	004772	CMP	#-2-1&177775,TEMP	;COMPARE LITERAL TO TEMP
1596	007160	001401			BEQ	.+4	;TEST FOR EQUAL
1597	007162	000000			HLT		;BIC INSTRUCTION FAILED
1598	007164	000240			SCOPE		
1599	007166	012767	177775	004756	MOV	#177775,TEMP	;MOV 177775 TO TEMP
1600	007174	052767	000002	004750	BIS	#2,TEMP	;SELECTIVE SET TEMP
1601	007202	022767	177777	004742	CMP	#177775!2,TEMP	;COMPARE LITERAL TO TEMP
1602	007210	001401			BEQ	.+4	;TEST FOR EQUAL
1603	007212	000000			HLT		;BIS INSTRUCTION FAILED
1604	007214	000240			SCOPE		

1605		000004			N=N+N	
1606		177773			M=M+M+1	
1607	007216	012700	000004		MOV #4,RO	;MOV 4 TO RO
1608	007222	042700	177773		BIC #177773,RO	;SELECTIVELY CLEAR RO
1609	007226	022700	000004		CMP #-177773-1&4,RO	;COMPARE LITERAL TO RO
1610	007232	001401			BEQ .+4	;TEST FOR EQUAL
1611	007234	000000			HLT	;BIC INSTRUCTION FAILED
1612	007236	000240			SCOPE	
1613	007240	012700	000004		MOV #4,RO	;MOV 4 TO RO
1614	007244	052700	177773		BIS #177773,RO	;SELECTIVE SET RO
1615	007250	022700	177777		CMP #4:177773,RO	;COMPARE LITERAL TO RO
1616	007254	001401			BEQ .+4	;TEST FOR EQUAL
1617	007256	000000			HLT	;BIS INSTRUCTION FAILED
1618	007260	000240			SCOPE	
1619	007262	012700	177773		MOV #177773,RO	;MOV 177773 TO RO
1620	007266	042700	000004		BIC #4,RO	;SELECTIVELY CLEAR RO
1621	007272	022700	177773		CMP #-4-1&177773,RO	;COMPARE LITERAL TO RO
1622	007276	001401			BEQ .+4	;TEST FOR EQUAL
1623	007300	000000			HLT	;BIC INSTRUCTION FAILED
1624	007302	000240			SCOPE	
1625	007304	012700	177773		MOV #177773,RO	;MOV 177773 TO RO
1626	007310	052700	000004		BIS #4,RO	;SELECTIVE SET RO
1627	007314	022700	177777		CMP #177773!4,RO	;COMPARE LITERAL TO RO
1628	007320	001401			BEQ .+4	;TEST FOR EQUAL
1629	007322	000000			HLT	;BIS INSTRUCTION FAILED
1630	007324	000240			SCOPE	
1631	007326	012767	000004	004616	MOV #4,TEMP	;MOV 4 TO TEMP
1632	007334	042767	177773	004610	BIC #177773,TEMP	;SELECTIVELY CLEAR TEMP
1633	007342	022767	000004	004602	CMP #-177773-1&4,TEMP	;COMPARE LITERAL TO TEMP
1634	007350	001401			BEQ .+4	;TEST FOR EQUAL
1635	007352	000000			HLT	;BIC INSTRUCTION FAILED
1636	007354	000240			SCOPE	
1637	007356	012767	000004	004566	MOV #4,TEMP	;MOV 4 TO TEMP
1638	007364	052767	177773	004560	BIS #177773,TEMP	;SELECTIVE SET TEMP
1639	007372	022767	177777	004552	CMP #4!177773,TEMP	;COMPARE LITERAL TO TEMP
1640	007400	001401			BEQ .+4	;TEST FOR EQUAL
1641	007402	000000			HLT	;BIS INSTRUCTION FAILED
1642	007404	000240			SCOPE	
1643	007406	012767	177773	004536	MOV #177773,TEMP	;MOV 177773 TO TEMP
1644	007414	042767	000004	004530	BIC #4,TEMP	;SELECTIVELY CLEAR TEMP
1645	007422	022767	177773	004522	CMP #-4-1&177773,TEMP	;COMPARE LITERAL TO TEMP
1646	007430	001401			BEQ .+4	;TEST FOR EQUAL
1647	007432	000000			HLT	;BIC INSTRUCTION FAILED
1648	007434	000240			SCOPE	
1649	007436	012767	177773	004506	MOV #177773,TEMP	;MOV 177773 TO TEMP
1650	007444	052767	000004	004500	BIS #4,TEMP	;SELECTIVE SET TEMP
1651	007452	022767	177777	004472	CMP #177773!4,TEMP	;COMPARE LITERAL TO TEMP
1652	007460	001401			BEQ .+4	;TEST FOR EQUAL
1653	007462	000000			HLT	;BIS INSTRUCTION FAILED
1654	007464	000240			SCOPE	
1655		000010			N=N+N	
1656		177767			M=M+M+1	
1657	007466	012700	000010		MOV #10,RO	;MOV 10 TO RO
1658	007472	042700	177767		BIC #177767,RO	;SELECTIVELY CLEAR RO
1659	007476	022700	000010		CMP #-177767-1&10,RO	;COMPARE LITERAL TO RO
1660	007502	001401			BEQ .+4	;TEST FOR EQUAL

# J03

.MAIN. MACY11 27(732) 01-OCT-76 10:26 PAGE 37  
OOIA.P11

1661	007504	000000		HLT					;BIC INSTRUCTION FAILED
1662	007506	000240		SCOPE					
1663	007510	012700	000010	MOV	#10,RO				;MOV 10 TO RO
1664	007514	052700	177767	BIS	#177767,RO				;SELECTIVE SET RO
1665	007520	022700	177777	CMP	#10!177767,RO				;COMPARE LITERAL TO RO
1666	007524	001401		BEQ	.+4				;TEST FOR EQUAL
1667	007526	000000		HLT					;BIS INSTRUCTION FAILED
1668	007530	000240		SCOPE					
1669	007532	012700	177767	MOV	#177767,RO				;MOV 177767 TO RO
1670	007536	042700	000010	BIC	#10,RO				;SELECTIVELY CLEAR RO
1671	007542	022700	177767	CMP	#-10-1&177767,RO				;COMPARE LITERAL TO RO
1672	007546	001401		BEQ	.+4				;TEST FOR EQUAL
1673	007550	000000		HLT					;BIC INSTRUCTION FAILED
1674	007552	000240		SCOPE					
1675	007554	012700	177767	MOV	#177767,RO				;MOV 177767 TO RO
1676	007560	052700	000010	BIS	#10,RO				;SELECTIVE SET RO
1677	007564	022700	177777	CMP	#177767!10,RO				;COMPARE LITERAL TO RO
1678	007570	001401		BEQ	.+4				;TEST FOR EQUAL
1679	007572	000000		HLT					;BIS INSTRUCTION FAILED
1680	007574	000240		SCOPE					
1681	007576	012767	000010	MOV	#10,TEMP				;MOV 10 TO TEMP
1682	007604	042767	177767	BIC	#177767,TEMP				;SELECTIVELY CLEAR TEMP
1683	007612	022767	000010	CMP	#-177767-1&10,TEMP				;COMPARE LITERAL TO TEMP
1684	007620	001401		BEQ	.+4				;TEST FOR EQUAL
1685	007622	000000		HLT					;BIC INSTRUCTION FAILED
1686	007624	000240		SCOPE					
1687	007626	012767	000010	MOV	#10,TEMP				;MOV 10 TO TEMP
1688	007634	052767	177767	BIS	#177767,TEMP				;SELECTIVE SET TEMP
1689	007642	022767	177777	CMP	#10!177767,TEMP				;COMPARE LITERAL TO TEMP
1690	007650	001401		BEQ	.+4				;TEST FOR EQUAL
1691	007652	000000		HLT					;BIS INSTRUCTION FAILED
1692	007654	000240		SCOPE					
1693	007656	012767	177767	MOV	#177767,TEMP				;MOV 177767 TO TEMP
1694	007664	042767	000010	BIC	#10,TEMP				;SELECTIVELY CLEAR TEMP
1695	007672	022767	177767	CMP	#-10-1&177767,TEMP				;COMPARE LITERAL TO TEMP
1696	007700	001401		BEQ	.+4				;TEST FOR EQUAL
1697	007702	000000		HLT					;BIC INSTRUCTION FAILED
1698	007704	000240		SCOPE					
1699	007706	012767	177767	MOV	#177767,TEMP				;MOV 177767 TO TEMP
1700	007714	052767	000010	BIS	#10,TEMP				;SELECTIVE SET TEMP
1701	007722	022767	177777	CMP	#177767!10,TEMP				;COMPARE LITERAL TO TEMP
1702	007730	001401		BEQ	.+4				;TEST FOR EQUAL
1703	007732	000000		HLT					;BIS INSTRUCTION FAILED
1704	007734	000240		SCOPE					
1705		000020		N=N+N					
1706		177757		M=M+M+1					
1707	007736	012700	000020	MOV	#20,RO				;MOV 20 TO RO
1708	007742	042700	177757	BIC	#177757,RO				;SELECTIVELY CLEAR RO
1709	007746	022700	000020	CMP	#-177757-1&20,RO				;COMPARE LITERAL TO RO
1710	007752	001401		BEQ	.+4				;TEST FOR EQUAL
1711	007754	000000		HLT					;BIC INSTRUCTION FAILED
1712	007756	000240		SCOPE					
1713	007760	012700	000020	MOV	#20,RO				;MOV 20 TO RO
1714	007764	052700	177757	BIS	#177757,RO				;SELECTIVE SET RO
1715	007770	022700	177777	CMP	#20!177757,RO				;COMPARE LITERAL TO RO
1716	007774	001401		BEQ	.+4				;TEST FOR EQUAL



# K03

MAIN MACY11 27(732) 01-OCT-76 10:26 PAGE 38  
DJIA.P11

1717	007776	000000			HLT		;BIS INSTRUCTION FAILED
1718	010000	000240			SCOPE		
1719	010002	012700	177757		MOV	#177757,RO	;MOV 177757 TO RO
1720	010006	042700	000020		BIC	#20,RO	;SELECTIVELY CLEAR RO
1721	010012	022700	177757		CMP	#-20-1&177757,RO	;COMPARE LITERAL TO RO
1722	010016	001401			BEQ	+.4	;TEST FOR EQUAL
1723	010020	000000			HLT		;BIC INSTRUCTION FAILED
1724	010022	000240			SCOPE		
1725	010024	012700	177757		MOV	#177757,RO	;MOV 177757 TO RO
1726	010030	052700	000020		BIS	#20,RO	;SELECTIVE SET RO
1727	010034	022700	177777		CMP	#177757!20,RO	;COMPARE LITERAL TO RO
1728	010040	001401			BEQ	+.4	;TEST FOR EQUAL
1729	010042	000000			HLT		;BIS INSTRUCTION FAILED
1730	010044	000240			SCOPE		
1731	010046	012767	000020	004076	MOV	#20,TEMP	;MOV 20 TO TEMP
1732	010054	042767	177757	004070	BIC	#177757,TEMP	;SELECTIVELY CLEAR TEMP
1733	010062	022767	000020	004062	CMP	#-177757-1&20,TEMP	;COMPARE LITERAL TO TEMP
1734	010070	001401			BEQ	+.4	;TEST FOR EQUAL
1735	010072	000000			HLT		;BIC INSTRUCTION FAILED
1736	010074	000240			SCOPE		
1737	010076	012767	000020	004046	MOV	#20,TEMP	;MOV 20 TO TEMP
1738	010104	052767	177757	004040	BIS	#177757,TEMP	;SELECTIVE SET TEMP
1739	010112	022767	177777	004032	CMP	#20!177757,TEMP	;COMPARE LITERAL TO TEMP
1740	010120	001401			BEQ	+.4	;TEST FOR EQUAL
1741	010122	000000			HLT		;BIS INSTRUCTION FAILED
1742	010124	000240			SCOPE		
1743	010126	012767	177757	004016	MOV	#177757,TEMP	;MOV 177757 TO TEMP
1744	010134	042767	000020	004010	BIC	#20,TEMP	;SELECTIVELY CLEAR TEMP
1745	010142	022767	177757	004002	CMP	#-20-1&177757,TEMP	;COMPARE LITERAL TO TEMP
1746	010150	001401			BEQ	+.4	;TEST FOR EQUAL
1747	010152	000000			HLT		;BIC INSTRUCTION FAILED
1748	010154	000240			SCOPE		
1749	010156	012767	177757	003766	MOV	#177757,TEMP	;MOV 177757 TO TEMP
1750	010164	052767	000020	003760	BIS	#20,TEMP	;SELECTIVE SET TEMP
1751	010172	022767	177777	003752	CMP	#177757!20,TEMP	;COMPARE LITERAL TO TEMP
1752	010200	001401			BEQ	+.4	;TEST FOR EQUAL
1753	010202	000000			HLT		;BIS INSTRUCTION FAILED
1754	010204	000240			SCOPE		
1755		000040			N=N+N		
1756		177737			M=M+M+1		
1757	010206	012700	000040		MOV	#40,RO	;MOV 40 TO RO
1758	010212	042700	177737		BIC	#177737,RO	;SELECTIVELY CLEAR RO
1759	010216	022700	000040		CMP	#-177737-1&40,RO	;COMPARE LITERAL TO RO
1760	010222	001401			BEQ	+.4	;TEST FOR EQUAL
1761	010224	000000			HLT		;BIC INSTRUCTION FAILED
1762	010226	000240			SCOPE		
1763	010230	012700	000040		MOV	#40,RO	;MOV 40 TO RO
1764	010234	052700	177737		BIS	#177737,RO	;SELECTIVE SET RO
1765	010240	022700	177777		CMP	#40!177737,RO	;COMPARE LITERAL TO RO
1766	010244	001401			BEQ	+.4	;TEST FOR EQUAL
1767	010246	000000			HLT		;BIS INSTRUCTION FAILED
1768	010250	000240			SCOPE		
1769	010252	012700	177737		MOV	#177737,RO	;MOV 177737 TO RO
1770	010256	042700	000040		BIC	#40,RO	;SELECTIVELY CLEAR RO
1771	010262	022700	177737		CMP	#-40-1&177737,RO	;COMPARE LITERAL TO RO
1772	010266	001401			BEQ	+.4	;TEST FOR EQUAL

# L03

1773	010270	000000		HLT		;BIC INSTRUCTION FAILED
1774	010272	000240		SCOPE		
1775	010274	012700	177737	MOV	#177737,RO	;MOV 177737 TO RO
1776	010300	052700	000040	BIS	#40,RO	;SELECTIVE SET RO
1777	010304	022700	177777	CMP	#177737!40,RO	;COMPARE LITERAL TO RO
1778	010310	001401		BEQ	+.4	;TEST FOR EQUAL
1779	010312	000000		HLT		;BIC INSTRUCTION FAILED
1780	010314	000240		SCOPE		
1781	010316	012767	000040 003626	MOV	#40,TEMP	;MOV 40 TO TEMP
1782	010324	042767	177737 003520	BIC	#177737,TEMP	;SELECTIVELY CLEAR TEMP
1783	010332	022767	000040 003612	CMP	#-177737-1&40,TEMP	;COMPARE LITERAL TO TEMP
1784	010340	001401		BEQ	+.4	;TEST FOR EQUAL
1785	010342	000000		HLT		;BIC INSTRUCTION FAILED
1786	010344	000240		SCOPE		
1787	010346	012767	000040 003576	MOV	#40,TEMP	;MOV 40 TO TEMP
1788	010354	052767	177737 003570	BIS	#177737,TEMP	;SELECTIVE SET TEMP
1789	010362	022767	177777 003562	CMP	#40!177737,TEMP	;COMPARE LITERAL TO TEMP
1790	010370	001401		BEQ	+.4	;TEST FOR EQUAL
1791	010372	000000		HLT		;BIC INSTRUCTION FAILED
1792	010374	000240		SCOPE		
1793	010376	012767	177737 003546	MOV	#177737,TEMP	;MOV 177737 TO TEMP
1794	010404	042767	000040 003540	BIC	#40,TEMP	;SELECTIVELY CLEAR TEMP
1795	010412	022767	177737 003532	CMP	#-40-1&177737,TEMP	;COMPARE LITERAL TO TEMP
1796	010420	001401		BEQ	+.4	;TEST FOR EQUAL
1797	010422	000000		HLT		;BIC INSTRUCTION FAILED
1798	010424	000240		SCOPE		
1799	010426	012767	177737 003516	MOV	#177737,TEMP	;MOV 177737 TO TEMP
1800	010434	052767	000040 003510	BIS	#40,TEMP	;SELECTIVE SET TEMP
1801	010442	022767	177777 003502	CMP	#177737!40,TEMP	;COMPARE LITERAL TO TEMP
1802	010450	001401		BEQ	+.4	;TEST FOR EQUAL
1803	010452	000000		HLT		;BIC INSTRUCTION FAILED
1804	010454	000240		SCOPE		
1805		000100		N=N+N		
1806		177677		M=M+M+1		
1807	010456	012700	000100	MOV	#100,RO	;MOV 100 TO RO
1808	010462	042700	177677	BIC	#177677,RO	;SELECTIVELY CLEAR RO
1809	010466	022700	000100	CMP	#-177677-1&100,RO	;COMPARE LITERAL TO RO
1810	010472	001401		BEQ	+.4	;TEST FOR EQUAL
1811	010474	000000		HLT		;BIC INSTRUCTION FAILED
1812	010476	000240		SCOPE		
1813	010500	012700	000100	MOV	#100,RO	;MOV 100 TO RO
1814	010504	052700	177677	BIS	#177677,RO	;SELECTIVE SET RO
1815	010510	022700	177777	CMP	#100!177677,RO	;COMPARE LITERAL TO RO
1816	010514	001401		BEQ	+.4	;TEST FOR EQUAL
1817	010516	000000		HLT		;BIC INSTRUCTION FAILED
1818	010520	000240		SCOPE		
1819	010522	012700	177677	MOV	#177677,RO	;MOV 177677 TO RO
1820	010526	042700	000100	BIC	#100,RO	;SELECTIVELY CLEAR RO
1821	010532	022700	177677	CMP	#-100-1&177677,RO	;COMPARE LITERAL TO RO
1822	010536	001401		BEQ	+.4	;TEST FOR EQUAL
1823	010540	000000		HLT		;BIC INSTRUCTION FAILED
1824	010542	000240		SCOPE		
1825	010544	012700	177677	MOV	#177677,RO	;MOV 177677 TO RO
1826	010550	052700	000100	BIS	#100,RO	;SELECTIVE SET RO
1827	010554	022700	177777	CMP	#177677!100,RO	;COMPARE LITERAL TO RO
1828	010560	001401		BEQ	+.4	;TEST FOR EQUAL

# M03

1829	010562	000000			HLT				;BIS INSTRUCTION FAILED
1830	010564	000240			SCOPE				
1831	010566	012767	000100	003356	MOV	#100,TEMP			;MOV 100 TO TEMP
1832	010574	042767	177677	003350	BIC	#177677,TEMP			;SELECTIVELY CLEAR TEMP
1833	010602	022767	000100	003342	CMP	#-177677-1&100,TEMP			;COMPARE LITERAL TO TEMP
1834	010610	001401			BEQ	+.4			;TEST FOR EQUAL
1835	010612	000000			HLT				;BIC INSTRUCTION FAILED
1836	010614	000240			SCOPE				
1837	010616	012767	000100	003326	MOV	#100,TEMP			;MOV 100 TO TEMP
1838	010624	052767	177677	003320	BIS	#177677,TEMP			;SELECTIVE SET TEMP
1839	010632	022767	177777	003312	CMP	#100!177677,TEMP			;COMPARE LITERAL TO TEMP
1840	010640	001401			BEQ	+.4			;TEST FOR EQUAL
1841	010642	000000			HLT				;BIS INSTRUCTION FAILED
1842	010644	000240			SCOPE				
1843	010646	012767	177677	003276	MOV	#177677,TEMP			;MOV 177677 TO TEMP
1844	010654	042767	000100	003270	BIC	#100,TEMP			;SELECTIVELY CLEAR TEMP
1845	010662	022767	177677	003262	CMP	#-100-1&177677,TEMP			;COMPARE LITERAL TO TEMP
1846	010670	001401			BEQ	+.4			;TEST FOR EQUAL
1847	010672	000000			HLT				;BIC INSTRUCTION FAILED
1848	010674	000240			SCOPE				
1849	010676	012767	177677	003246	MOV	#177677,TEMP			;MOV 177677 TO TEMP
1850	010704	052767	000100	003240	BIS	#100,TEMP			;SELECTIVE SET TEMP
1851	010712	022767	177777	003232	CMP	#177677!100,TEMP			;COMPARE LITERAL TO TEMP
1852	010720	001401			BEQ	+.4			;TEST FOR EQUAL
1853	010722	000000			HLT				;BIS INSTRUCTION FAILED
1854	010724	000240			SCOPE				
1855		000200			N=N+N				
1856		177577			M=M+M+1				
1857	010726	012700	000200		MOV	#200,RO			;MOV 200 TO RO
1858	010732	042700	177577		BIC	#177577,RO			;SELECTIVELY CLEAR RO
1859	010736	022700	000200		CMP	#-177577-1&200,RO			;COMPARE LITERAL TO RO
1860	010742	001401			BEQ	+.4			;TEST FOR EQUAL
1861	010744	000000			HLT				;BIC INSTRUCTION FAILED
1862	010746	000240			SCOPE				
1863	010750	012700	000200		MOV	#200,RO			;MOV 200 TO RO
1864	010754	052700	177577		BIS	#177577,RO			;SELECTIVE SET RO
1865	010760	022700	177777		CMP	#200!177577,RO			;COMPARE LITERAL TO RO
1866	010764	001401			BEQ	+.4			;TEST FOR EQUAL
1867	010766	000000			HLT				;BIS INSTRUCTION FAILED
1868	010770	000240			SCOPE				
1869	010772	012700	177577		MOV	#177577,RO			;MOV 177577 TO RO
1870	010776	042700	000200		BIC	#200,RO			;SELECTIVELY CLEAR RO
1871	011002	022700	177577		CMP	#-200-1&177577,RO			;COMPARE LITERAL TO RO
1872	011006	001401			BEQ	+.4			;TEST FOR EQUAL
1873	011010	000000			HLT				;BIC INSTRUCTION FAILED
1874	011012	000240			SCOPE				
1875	011014	012700	177577		MOV	#177577,RO			;MOV 177577 TO RO
1876	011020	052700	000200		BIS	#200,RO			;SELECTIVE SET RO
1877	011024	022700	177777		CMP	#177577!200,RO			;COMPARE LITERAL TO RO
1878	011030	001401			BEQ	+.4			;TEST FOR EQUAL
1879	011032	000000			HLT				;BIS INSTRUCTION FAILED
1880	011034	000240			SCOPE				
1881	011036	012767	000200	003106	MOV	#200,TEMP			;MOV 200 TO TEMP
1882	011044	042767	177577	003100	BIC	#177577,TEMP			;SELECTIVELY CLEAR TEMP
1883	011052	022767	000200	003072	CMP	#-177577-1&200,TEMP			;COMPARE LITERAL TO TEMP
1884	011060	001401			BEQ	+.4			;TEST FOR EQUAL

# NO3

1895	011062	000000			HLT				;BIC INSTRUCTION FAILED
1896	011064	000240			SCOPE				
1897	011066	012767	000200	003056	MOV	#200,TEMP			;MOV 200 TO TEMP
1898	011074	052767	177577	003050	BIS	#177577,TEMP			;SELECTIVE SET TEMP
1899	011102	022767	177777	003042	CMP	#200!177577,TEMP			;COMPARE LITERAL TO TEMP
1890	011110	001401			BEQ	+.4			;TEST FOR EQUAL
1891	011112	000000			HLT				;BIC INSTRUCTION FAILED
1892	011114	000240			SCOPE				
1893	011116	012767	177577	003026	MOV	#177577,TEMP			;MOV 177577 TO TEMP
1894	011124	042767	000200	003020	BIC	#200,TEMP			;SELECTIVELY CLEAR TEMP
1895	011132	022767	177577	003012	CMP	#-200-1&177577,TEMP			;COMPARE LITERAL TO TEMP
1896	011140	001401			BEQ	+.4			;TEST FOR EQUAL
1897	011142	000000			HLT				;BIC INSTRUCTION FAILED
1898	011144	000240			SCOPE				
1899	011146	012767	177577	002776	MOV	#177577,TEMP			;MOV 177577 TO TEMP
1900	011154	052767	000200	002770	BIS	#200,TEMP			;SELECTIVE SET TEMP
1901	011162	022767	177777	002762	CMP	#177577!200,TEMP			;COMPARE LITERAL TO TEMP
1902	011170	001401			BEQ	+.4			;TEST FOR EQUAL
1903	011172	000000			HLT				;BIC INSTRUCTION FAILED
1904	011174	000240			SCOPE				
1905		000400			N=N+N				
1906		177377			M=M+M+1				
1907	011176	012700	000400		MOV	#400,RO			;MOV 400 TO RO
1908	011202	042700	177377		BIC	#177377,RO			;SELECTIVELY CLEAR RO
1909	011206	022 00	000400		CMP	#-177377-1&400,RO			;COMPARE LITERAL TO RO
1910	011212	001401			BEQ	+.4			;TEST FOR EQUAL
1911	011214	000000			HLT				;BIC INSTRUCTION FAILED
1912	011216	000240			SCOPE				
1913	011220	012700	000400		MOV	#400,RO			;MOV 400 TO RO
1914	011224	052700	177377		BIS	#177377,RO			;SELECTIVE SET RO
1915	011230	022700	177777		CMP	#400!177377,RO			;COMPARE LITERAL TO RO
1916	011234	001401			BEQ	+.4			;TEST FOR EQUAL
1917	011236	000000			HLT				;BIC INSTRUCTION FAILED
1918	011240	000240			SCOPE				
1919	011242	012700	177377		MOV	#177377,RO			;MOV 177377 TO RO
1920	011246	042700	000400		BIC	#400,RO			;SELECTIVELY CLEAR RO
1921	011252	022700	177377		CMP	#-400-1&177377,RO			;COMPARE LITERAL TO RO
1922	011256	001401			BEQ	+.4			;TEST FOR EQUAL
1923	011260	000000			HLT				;BIC INSTRUCTION FAILED
1924	011262	000240			SCOPE				
1925	011264	012700	177377		MOV	#177377,RO			;MOV 177377 TO RO
1926	011270	052700	000400		BIS	#400,RO			;SELECTIVE SET RO
1927	011274	022700	177777		CMP	#177377!400,RO			;COMPARE LITERAL TO RO
1928	011300	001401			BEQ	+.4			;TEST FOR EQUAL
1929	011302	000000			HLT				;BIC INSTRUCTION FAILED
1930	011304	000240			SCOPE				
1931	011306	012767	000400	002636	MOV	#400,TEMP			;MOV 400 TO TEMP
1932	011314	042767	177377	002630	BIC	#177377,TEMP			;SELECTIVELY CLEAR TEMP
1933	011322	022767	000400	002622	CMP	#-177377-1&400,TEMP			;COMPARE LITERAL TO TEMP
1934	011330	001401			BEQ	+.4			;TEST FOR EQUAL
1935	011332	000000			HLT				;BIC INSTRUCTION FAILED
1936	011334	000240			SCOPE				
1937	011336	012767	000400	002606	MOV	#400,TEMP			;MOV 400 TO TEMP
1938	011344	052767	177377	002600	BIS	#177377,TEMP			;SELECTIVE SET TEMP
1939	011352	022767	177777	002572	CMP	#400!177377,TEMP			;COMPARE LITERAL TO TEMP
1940	011360	001401			BEQ	+.4			;TEST FOR EQUAL

194	011362	000000			HLT				;BIS INSTRUCTION FAILED
194	011364	000240			SCOPE				
194	011366	012767	177377	002556	MOV	#177377,TEMP			;MOV 177377 TO TEMP
194	011374	042767	000400	002550	BIC	#400,TEMP			;SELECTIVELY CLEAR TEMP
194	011402	022767	177377	002542	CMP	#-400-18177377,TEMP			;COMPARE LITERAL TO TEMP
194	011410	001401			BEQ	.+4			;TEST FOR EQUAL
194	011412	000000			HLT				;BIS INSTRUCTION FAILED
194	011414	000240			SCOPE				
194	011416	012767	177377	002526	MOV	#177377,TEMP			;MOV 177377 TO TEMP
194	011424	052767	000400	002520	BIS	#400,TEMP			;SELECTIVE SET TEMP
194	011432	022767	177377	002512	CMP	#177377!400,TEMP			;COMPARE LITERAL TO TEMP
194	011440	001401			BEQ	.+4			;TEST FOR EQUAL
194	011442	000000			HLT				;BIS INSTRUCTION FAILED
194	011444	000240			SCOPE				
194		001000			N=N+N				
194		176777			M=M+M+1				
195	011446	012700	001000		MOV	#1000,RO			;MOV 1000 TO RO
195	011452	042700	176777		BIC	#176777,RO			;SELECTIVELY CLEAR RO
195	011456	022700	001000		CMP	#-176777-181000,RO			;COMPARE LITERAL TO RO
195	011462	001401			BEQ	.+4			;TEST FOR EQUAL
195	011464	000000			HLT				;BIS INSTRUCTION FAILED
195	011466	000240			SCOPE				
195	011470	012700	001000		MOV	#1000,RO			;MOV 1000 TO RO
195	011474	052700	176777		BIS	#176777,RO			;SELECTIVE SET RO
195	011500	022700	177777		CMP	#1000!176777,RO			;COMPARE LITERAL TO RO
195	011504	001401			BEQ	.+4			;TEST FOR EQUAL
195	011506	000000			HLT				;BIS INSTRUCTION FAILED
195	011510	000240			SCOPE				
195	011512	012700	176777		MOV	#176777,RO			;MOV 176777 TO RO
195	011516	042700	001000		BIC	#1000,RO			;SELECTIVELY CLEAR RO
195	011522	022700	176777		CMP	#-1000-18176777,RO			;COMPARE LITERAL TO RO
195	011526	001401			BEQ	.+4			;TEST FOR EQUAL
195	011530	000000			HLT				;BIS INSTRUCTION FAILED
195	011532	000240			SCOPE				
195	011534	012700	176777		MOV	#176777,RO			;MOV 176777 TO RO
195	011540	052700	001000		BIS	#1000,RO			;SELECTIVE SET RO
195	011544	022700	177777		CMP	#176777!1000,RO			;COMPARE LITERAL TO RO
195	011550	001401			BEQ	.+4			;TEST FOR EQUAL
195	011552	000000			HLT				;BIS INSTRUCTION FAILED
195	011554	000240			SCOPE				
195	011556	012767	001000	002366	MOV	#1000,TEMP			;MOV 1000 TO TEMP
195	011564	042767	176777	002360	BIC	#176777,TEMP			;SELECTIVELY CLEAR TEMP
195	011572	022767	001000	002352	CMP	#-176777-181000,TEMP			;COMPARE LITERAL TO TEMP
195	011600	001401			BEQ	.+4			;TEST FOR EQUAL
195	011602	000000			HLT				;BIS INSTRUCTION FAILED
195	011604	000240			SCOPE				
195	011606	012767	001000	002336	MOV	#1000,TEMP			;MOV 1000 TO TEMP
195	011614	052767	176777	002330	BIS	#176777,TEMP			;SELECTIVE SET TEMP
195	011622	022767	177777	002322	CMP	#1000!176777,TEMP			;COMPARE LITERAL TO TEMP
195	011630	001401			BEQ	.+4			;TEST FOR EQUAL
195	011632	000000			HLT				;BIS INSTRUCTION FAILED
195	011634	000240			SCOPE				
195	011636	012767	176777	002306	MOV	#176777,TEMP			;MOV 176777 TO TEMP
195	011644	042767	001000	002300	BIC	#1000,TEMP			;SELECTIVELY CLEAR TEMP
195	011652	022767	176777	002272	CMP	#-1000-18176777,TEMP			;COMPARE LITERAL TO TEMP
195	011660	001401			BEQ	.+4			;TEST FOR EQUAL

1997	011662	000000			HLT		;BIC INSTRUCTION FAILED
1998	011664	000240			SCOPE		
1999	011666	012767	176777	002256	MOV	#176777,TEMP	;MOV 176777 TO TEMP
2000	011674	052767	001000	002250	BIS	#1000,TEMP	;SELECTIVE SET TEMP
2001	011702	022767	177777	002242	CMP	#176777!1000,TEMP	;COMPARE LITERAL TO TEMP
2002	011710	001401			BEQ	+.4	;TEST FOR EQUAL
2003	011712	000000			HLT		;BIS INSTRUCTION FAILED
2004	011714	000240			SCOPE		
2005		002000			N=N+N		
2006		175777			M=M+M+1		
2007	011716	012700	002000		MOV	#2000,RO	;MOV 2000 TO RO
2008	011722	042700	175777		BIC	#175777,RO	;SELECTIVELY CLEAR RO
2009	011726	022700	002000		CMP	#-175777-1&2000,RO	;COMPARE LITERAL TO RO
2010	011732	001401			BEQ	+.4	;TEST FOR EQUAL
2011	011734	000000			HLT		;BIC INSTRUCTION FAILED
2012	011736	000240			SCOPE		
2013	011740	012700	002000		MOV	#2000,RO	;MOV 2000 TO RO
2014	011744	052700	175777		BIS	#175777,RO	;SELECTIVE SET RO
2015	011750	022700	177777		CMP	#2000!175777,RO	;COMPARE LITERAL TO RO
2016	011754	001401			BEQ	+.4	;TEST FOR EQUAL
2017	011756	000000			HLT		;BIS INSTRUCTION FAILED
2018	011760	000240			SCOPE		
2019	011762	012700	175777		MOV	#175777,RO	;MOV 175777 TO RO
2020	011766	042700	002000		BIC	#2000,RO	;SELECTIVELY CLEAR RO
2021	011772	022700	175777		CMP	#-2000-1&175777,RO	;COMPARE LITERAL TO RO
2022	011776	001401			BEQ	+.4	;TEST FOR EQUAL
2023	012000	000000			HLT		;BIC INSTRUCTION FAILED
2024	012002	000240			SCOPE		
2025	012004	012700	175777		MOV	#175777,RO	;MOV 175777 TO RO
2026	012010	052700	002000		BIS	#2000,RO	;SELECTIVE SET RO
2027	012014	022700	177777		CMP	#175777!2000,RO	;COMPARE LITERAL TO RO
2028	012020	001401			BEQ	+.4	;TEST FOR EQUAL
2029	012022	000000			HLT		;BIS INSTRUCTION FAILED
2030	012024	000240			SCOPE		
2031	012026	012767	002000	002116	MOV	#2000,TEMP	;MOV 2000 TO TEMP
2032	012034	042767	175777	002110	BIC	#175777,TEMP	;SELECTIVELY CLEAR TEMP
2033	012042	022767	002000	002102	CMP	#-175777-1&2000,TEMP	;COMPARE LITERAL TO TEMP
2034	012050	001401			BEQ	+.4	;TEST FOR EQUAL
2035	012052	000000			HLT		;BIC INSTRUCTION FAILED
2036	012054	000240			SCOPE		
2037	012056	012767	002000	002066	MOV	#2000,TEMP	;MOV 2000 TO TEMP
2038	012064	052767	175777	002060	BIS	#175777,TEMP	;SELECTIVE SET TEMP
2039	012072	022767	177777	002052	CMP	#2000!175777,TEMP	;COMPARE LITERAL TO TEMP
2040	012100	001401			BEQ	+.4	;TEST FOR EQUAL
2041	012102	000000			HLT		;BIS INSTRUCTION FAILED
2042	012104	000240			SCOPE		
2043	012106	012767	175777	002036	MOV	#175777,TEMP	;MOV 175777 TO TEMP
2044	012114	042767	002000	002030	BIC	#2000,TEMP	;SELECTIVELY CLEAR TEMP
2045	012122	022767	175777	002022	CMP	#-2000-1&175777,TEMP	;COMPARE LITERAL TO TEMP
2046	012130	001401			BEQ	+.4	;TEST FOR EQUAL
2047	012132	000000			HLT		;BIC INSTRUCTION FAILED
2048	012134	000240			SCOPE		
2049	012136	012767	175777	002006	MOV	#175777,TEMP	;MOV 175777 TO TEMP
2050	012144	052767	002000	002000	BIS	#2000,TEMP	;SELECTIVE SET TEMP
2051	012152	022767	177777	001772	CMP	#175777!2000,TEMP	;COMPARE LITERAL TO TEMP
2052	012160	001401			BEQ	+.4	;TEST FOR EQUAL

2053	012162	000000		HLT					;BIS INSTRUCTION FAILED
2054	012164	000240		SCOPE					
2055		004000		N=N+N					
2056		173777		M=M+M+1					
2057	012166	012700	004000	MOV	#4000,RO				;MOV 4000 TO RO
2058	012172	042700	173777	BIC	#173777,RO				;SELECTIVELY CLEAR RO
2059	012176	022700	004000	CMP	#-173777-184000,RO				;COMPARE LITERAL TO RO
2060	012202	001401		BEQ	.+4				;TEST FOR EQUAL
2061	012204	000000		HLT					;BIC INSTRUCTION FAILED
2062	012206	000240		SCOPE					
2063	012210	012700	004000	MOV	#4000,RO				;MOV 4000 TO RO
2064	012214	052700	173777	BIS	#173777,RO				;SELECTIVE SET RO
2065	012220	022700	177777	CMP	#4000!173777,RO				;COMPARE LITERAL TO RO
2066	012224	001401		BEQ	.+4				;TEST FOR EQUAL
2067	012226	000000		HLT					;BIS INSTRUCTION FAILED
2068	012230	000240		SCOPE					
2069	012232	012700	173777	MOV	#173777,RO				;MOV 173777 TO RO
2070	012236	042700	004000	BIC	#4000,RO				;SELECTIVELY CLEAR RO
2071	012242	022700	173777	CMP	#-4000-18173777,RO				;COMPARE LITERAL TO RO
2072	012246	001401		BEQ	.+4				;TEST FOR EQUAL
2073	012250	000000		HLT					;BIC INSTRUCTION FAILED
2074	012252	000240		SCOPE					
2075	012254	012700	173777	MOV	#173777,RO				;MOV 173777 TO RO
2076	012260	052700	004000	BIS	#4000,RO				;SELECTIVE SET RO
2077	012264	022700	177777	CMP	#173777!4000,RO				;COMPARE LITERAL TO RO
2078	012270	001401		BEQ	.+4				;TEST FOR EQUAL
2079	012272	000000		HLT					;BIS INSTRUCTION FAILED
2080	012274	000240		SCOPE					
2081	012276	012767	004000	MOV	#4000,TEMP				;MOV 4000 TO TEMP
2082	012304	042767	173777	BIC	#173777,TEMP				;SELECTIVELY CLEAR TEMP
2083	012312	022767	004000	CMP	#-173777-184000,TEMP				;COMPARE LITERAL TO TEMP
2084	012320	001401		BEQ	.+4				;TEST FOR EQUAL
2085	012322	000000		HLT					;BIC INSTRUCTION FAILED
2086	012324	000240		SCOPE					
2087	012326	012767	004000	MOV	#4000,TEMP				;MOV 4000 TO TEMP
2088	012334	052767	173777	BIS	#173777,TEMP				;SELECTIVE SET TEMP
2089	012342	022767	177777	CMP	#4000!173777,TEMP				;COMPARE LITERAL TO TEMP
2090	012350	001401		BEQ	.+4				;TEST FOR EQUAL
2091	012352	000000		HLT					;BIS INSTRUCTION FAILED
2092	012354	000240		SCOPE					
2093	012356	012767	173777	MOV	#173777,TEMP				;MOV 173777 TO TEMP
2094	012364	042767	004000	BIC	#4000,TEMP				;SELECTIVELY CLEAR TEMP
2095	012372	022767	173777	CMP	#-4000-18173777,TEMP				;COMPARE LITERAL TO TEMP
2096	012400	001401		BEQ	.+4				;TEST FOR EQUAL
2097	012402	000000		HLT					;BIC INSTRUCTION FAILED
2098	012404	000240		SCOPE					
2099	012406	012767	173777	MOV	#173777,TEMP				;MOV 173777 TO TEMP
2100	012414	052767	004000	BIS	#4000,TEMP				;SELECTIVE SET TEMP
2101	012422	022767	177777	CMP	#173777!4000,TEMP				;COMPARE LITERAL TO TEMP
2102	012430	001401		BEQ	.+4				;TEST FOR EQUAL
2103	012432	000000		HLT					;BIS INSTRUCTION FAILED
2104	012434	000240		SCOPE					
2105		010000		N=N+N					
2106		167777		M=M+M+1					
2107	012436	012700	010000	MOV	#10000,RO				;MOV 10000 TO RO
2108	012442	042700	167777	BIC	#167777,RO				;SELECTIVELY CLEAR RO



# E04

2109	012446	022700	010000		CMP	#-167777-1810000,RO	;COMPARE LITERAL TO RO
2110	012452	001401			BEQ	.+4	;TEST FOR EQUAL
2111	012454	000000			HLT		;BIC INSTRUCTION FAILED
2112	012456	000240			SCOPE		
2113	012460	012700	010000		MOV	#10000,RO	;MOV 10000 TO RO
2114	012464	052700	167777		BIS	#167777,RO	;SELECTIVE SET RO
2115	012470	022700	177777		CMP	#10000!167777,RO	;COMPARE LITERAL TO RO
2116	012474	001401			BEQ	.+4	;TEST FOR EQUAL
2117	012476	000000			HLT		;BIS INSTRUCTION FAILED
2118	012500	000240			SCOPE		
2119	012502	012700	167777		MOV	#167777,RO	;MOV 167777 TO RO
2120	012506	042700	010000		BIC	#10000,RO	;SELECTIVELY CLEAR RO
2121	012512	022700	167777		CMP	#-10000-18167777,RO	;COMPARE LITERAL TO RO
2122	012516	001401			BEQ	.+4	;TEST FOR EQUAL
2123	012520	000000			HLT		;BIC INSTRUCTION FAILED
2124	012522	000240			SCOPE		
2125	012524	012700	167777		MOV	#167777,RO	;MOV 167777 TO RO
2126	012530	052700	010000		BIS	#10000,RO	;SELECTIVE SET RO
2127	012534	022700	177777		CMP	#167777!10000,RO	;COMPARE LITERAL TO RO
2128	012540	001401			BEQ	.+4	;TEST FOR EQUAL
2129	012542	000000			HLT		;BIS INSTRUCTION FAILED
2130	012544	000240			SCOPE		
2131	012546	012767	010000	001376	MOV	#10000,TEMP	;MOV 10000 TO TEMP
2132	012554	042767	167777	001370	BIC	#167777,TEMP	;SELECTIVELY CLEAR TEMP
2133	012562	022767	010000	001362	CMP	#-167777-1810000,TEMP	;COMPARE LITERAL TO TEMP
2134	012570	001401			BEQ	.+4	;TEST FOR EQUAL
2135	012572	000000			HLT		;BIC INSTRUCTION FAILED
2136	012574	000240			SCOPE		
2137	012576	012767	010000	001346	MOV	#10000,TEMP	;MOV 10000 TO TEMP
2138	012604	052767	167777	001340	BIS	#167777,TEMP	;SELECTIVE SET TEMP
2139	012612	022767	177777	001332	CMP	#10000!167777,TEMP	;COMPARE LITERAL TO TEMP
2140	012620	001401			BEQ	.+4	;TEST FOR EQUAL
2141	012622	000000			HLT		;BIS INSTRUCTION FAILED
2142	012624	000240			SCOPE		
2143	012626	012767	167777	001316	MOV	#167777,TEMP	;MOV 167777 TO TEMP
2144	012634	042767	010000	001310	BIC	#10000,TEMP	;SELECTIVELY CLEAR TEMP
2145	012642	022767	167777	001302	CMP	#-10000-18167777,TEMP	;COMPARE LITERAL TO TEMP
2146	012650	001401			BEQ	.+4	;TEST FOR EQUAL
2147	012652	000000			HLT		;BIC INSTRUCTION FAILED
2148	012654	000240			SCOPE		
2149	012656	012767	167777	001266	MOV	#167777,TEMP	;MOV 167777 TO TEMP
2150	012664	052767	010000	001260	BIS	#10000,TEMP	;SELECTIVE SET TEMP
2151	012672	022767	177777	001252	CMP	#167777!10000,TEMP	;COMPARE LITERAL TO TEMP
2152	012700	001401			BEQ	.+4	;TEST FOR EQUAL
2153	012702	000000			HLT		;BIS INSTRUCTION FAILED
2154	012704	000240			SCOPE		
2155		020000			N=N+N		
2156		157777			M=M+M+1		
2157	012706	012700	020000		MOV	#20000,RO	;MOV 20000 TO RO
2158	012712	042700	157777		BIC	#157777,RO	;SELECTIVELY CLEAR RO
2159	012716	022700	020000		CMP	#-157777-1820000,RO	;COMPARE LITERAL TO RO
2160	012722	001401			BEQ	.+4	;TEST FOR EQUAL
2161	012724	000000			HLT		;BIC INSTRUCTION FAILED
2162	012726	000240			SCOPE		
2163	012730	012700	020000		MOV	#20000,RO	;MOV 20000 TO RO
2164	012734	052700	157777		BIS	#157777,RO	;SELECTIVE SET RO



# F04

2165	012740	022700	177777			CMP	#20000!157777,RO		;COMPARE LITERAL TO RO
2166	012744	001401				BEQ	.+4		;TEST FOR EQUAL
2167	012746	000000				HLT			;BIS INSTRUCTION FAILED
2168	012750	000240				SCOPE			
2169	012752	012700	157777			MOV	#157777,RO		;MOV 157777 TO RO
2170	012756	042700	020000			BIC	#20000,RO		;SELECTIVELY CLEAR RO
2171	012762	022700	157777			CMP	#-20000-1&157777,RO		;COMPARE LITERAL TO RO
2172	012766	001401				BEQ	.+4		;TEST FOR EQUAL
2173	012770	000000				HLT			;BIC INSTRUCTION FAILED
2174	012772	000240				SCOPE			
2175	012774	012700	157777			MOV	#157777,RO		;MOV 157777 TO RO
2176	013000	052700	020000			BIS	#20000,RO		;SELECTIVE SET RO
2177	013004	022700	177777			CMP	#157777!20000,RO		;COMPARE LITERAL TO RO
2178	013010	001401				BEQ	.+4		;TEST FOR EQUAL
2179	013012	000000				HLT			;BIS INSTRUCTION FAILED
2180	013014	000240				SCOPE			
2181	013016	012767	020000	001126		MOV	#20000,TEMP		;MOV 20000 TO TEMP
2182	013024	042767	157777	001120		BIC	#157777,TEMP		;SELECTIVELY CLEAR TEMP
2183	013032	022767	020000	001112		CMP	#-157777-1&20000,TEMP		;COMPARE LITERAL TO TEMP
2184	013040	001401				BEQ	.+4		;TEST FOR EQUAL
2185	013042	000000				HLT			;BIC INSTRUCTION FAILED
2186	013044	000240				SCOPE			
2187	013046	012767	020000	001076		MOV	#20000,TEMP		;MOV 20000 TO TEMP
2188	013054	052767	157777	001070		BIS	#157777,TEMP		;SELECTIVE SET TEMP
2189	013062	022767	177777	001062		CMP	#20000!157777,TEMP		;COMPARE LITERAL TO TEMP
2190	013070	001401				BEQ	.+4		;TEST FOR EQUAL
2191	013072	000000				HLT			;BIS INSTRUCTION FAILED
2192	013074	000240				SCOPE			
2193	013076	012767	157777	001046		MOV	#157777,TEMP		;MOV 157777 TO TEMP
2194	013104	042767	020000	001040		BIC	#20000,TEMP		;SELECTIVELY CLEAR TEMP
2195	013112	022767	157777	001032		CMP	#-20000-1&157777,TEMP		;COMPARE LITERAL TO TEMP
2196	013120	001401				BEQ	.+4		;TEST FOR EQUAL
2197	013122	000000				HLT			;BIC INSTRUCTION FAILED
2198	013124	000240				SCOPE			
2199	013126	012767	157777	001016		MOV	#157777,TEMP		;MOV 157777 TO TEMP
2200	013134	052767	020000	001010		BIS	#20000,TEMP		;SELECTIVE SET TEMP
2201	013142	022767	177777	001002		CMP	#157777!20000,TEMP		;COMPARE LITERAL TO TEMP
2202	013150	001401				BEQ	.+4		;TEST FOR EQUAL
2203	013152	000000				HLT			;BIS INSTRUCTION FAILED
2204	013154	000240				SCOPE			
2205		040000				N=N+N			
2206		137777				M=M+M+1			
2207	013156	012700	040000			MOV	#40000,RO		;MOV 40000 TO RO
2208	013162	042700	137777			BIC	#137777,RO		;SELECTIVELY CLEAR RO
2209	013166	022700	040000			CMP	#-137777-1&40000,RO		;COMPARE LITERAL TO RO
2210	013172	001401				BEQ	.+4		;TEST FOR EQUAL
2211	013174	000000				HLT			;BIC INSTRUCTION FAILED
2212	013176	000240				SCOPE			
2213	013200	012700	040000			MOV	#40000,RO		;MOV 40000 TO RO
2214	013204	052700	137777			BIS	#137777,RO		;SELECTIVE SET RO
2215	013210	022700	177777			CMP	#40000!137777,RO		;COMPARE LITERAL TO RO
2216	013214	001401				BEQ	.+4		;TEST FOR EQUAL
2217	013216	000000				HLT			;BIS INSTRUCTION FAILED
2218	013220	000240				SCOPE			
2219	013222	012700	137777			MOV	#137777,RO		;MOV 137777 TO RO
2220	013226	042700	040000			BIC	#40000,RO		;SELECTIVELY CLEAR RO

# G04

2221	013232	022700	137777		CMP	#-40000-1&137777,RO	;COMPARE LITERAL TO RO
2222	013236	001401			BEQ	.+4	;TEST FOR EQUAL
2223	013240	000000			HLT		;BIC INSTRUCTION FAILED
2224	013242	000240			SCOPE		
2225	013244	012700	137777		MOV	#137777,RO	;MOV 137777 TO RO
2226	013250	052700	040000		BIS	#40000,RO	;SELECTIVE SET RO
2227	013254	022700	177777		CMP	#137777!40000,RO	;COMPARE LITERAL TO RO
2228	013260	001401			BEQ	.+4	;TEST FOR EQUAL
2229	013262	000000			HLT		;BIS INSTRUCTION FAILED
2230	013264	000240			SCOPE		
2231	013266	012767	040000	000656	MOV	#40000,TEMP	;MOV 40000 TO TEMP
2232	013274	042767	137777	000650	BIC	#137777,TEMP	;SELECTIVELY CLEAR TEMP
2233	013302	022767	040000	000642	CMP	#-137777-1&40000,TEMP	;COMPARE LITERAL TO TEMP
2234	013310	001401			BEQ	.+4	;TEST FOR EQUAL
2235	013312	000000			HLT		;BIC INSTRUCTION FAILED
2236	013314	000240			SCOPE		
2237	013316	012767	040000	000626	MOV	#40000,TEMP	;MOV 40000 TO TEMP
2238	013324	052767	137777	000620	BIS	#137777,TEMP	;SELECTIVE SET TEMP
2239	013332	022767	177777	000612	CMP	#40000!137777,TEMP	;COMPARE LITERAL TO TEMP
2240	013340	001401			BEQ	.+4	;TEST FOR EQUAL
2241	013342	000000			HLT		;BIS INSTRUCTION FAILED
2242	013344	000240			SCOPE		
2243	013346	012767	137777	000576	MOV	#137777,TEMP	;MOV 137777 TO TEMP
2244	013354	042767	040000	000570	BIC	#40000,TEMP	;SELECTIVELY CLEAR TEMP
2245	013362	022767	137777	000562	CMP	#-40000-1&137777,TEMP	;COMPARE LITERAL TO TEMP
2246	013370	001401			BEQ	.+4	;TEST FOR EQUAL
2247	013372	000000			HLT		;BIC INSTRUCTION FAILED
2248	013374	000240			SCOPE		
2249	013376	012767	137777	000546	MOV	#137777,TEMP	;MOV 137777 TO TEMP
2250	013404	052767	040000	000540	BIS	#40000,TEMP	;SELECTIVE SET TEMP
2251	013412	022767	177777	000532	CMP	#137777!40000,TEMP	;COMPARE LITERAL TO TEMP
2252	013420	001401			BEQ	.+4	;TEST FOR EQUAL
2253	013422	000000			HLT		;BIS INSTRUCTION FAILED
2254	013424	000240			SCOPE		
2255		100000			N=N+N		
2256		077777			M=M+M+1		
2257	013426	012700	100000		MOV	#100000,RO	;MOV 100000 TO RO
2258	013432	042700	077777		BIC	#77777,RO	;SELECTIVELY CLEAR RO
2259	013436	022700	100000		CMP	#-77777-1&100000,RO	;COMPARE LITERAL TO RO
2260	013442	001401			BEQ	.+4	;TEST FOR EQUAL
2261	013444	000000			HLT		;BIC INSTRUCTION FAILED
2262	013446	000240			SCOPE		
2263	013450	012700	100000		MOV	#100000,RO	;MOV 100000 TO RO
2264	013454	052700	077777		BIS	#77777,RO	;SELECTIVE SET RO
2265	013460	022700	177777		CMP	#100000!77777,RO	;COMPARE LITERAL TO RO
2266	013464	001401			BEQ	.+4	;TEST FOR EQUAL
2267	013466	000000			HLT		;BIS INSTRUCTION FAILED
2268	013470	000240			SCOPE		
2269	013472	012700	077777		MOV	#77777,RO	;MOV 77777 TO RO
2270	013476	042700	100000		BIC	#100000,RO	;SELECTIVELY CLEAR RO
2271	013502	022700	077777		CMP	#-100000-1&77777,RO	;COMPARE LITERAL TO RO
2272	013506	001401			BEQ	.+4	;TEST FOR EQUAL
2273	013510	000000			HLT		;BIC INSTRUCTION FAILED
2274	013512	000240			SCOPE		
2275	013514	012700	077777		MOV	#77777,RO	;MOV 77777 TO RO
2276	013520	052700	100000		BIS	#100000,RO	;SELECTIVE SET RO

# H04

2277	013524	022700	177777		CMP	#77777!100000,RO		;COMPARE LITERAL TO RO
2278	013530	001401			BEQ	.+4		;TEST FOR EQUAL
2279	013532	000000			HLT			;BIS INSTRUCTION FAILED
2280	013534	000240			SCOPE			
2281	013536	012767	100000	000406	MOV	#100000,TEMP		;MOV 100000 TO TEMP
2282	013544	042767	077777	000400	BIC	#77777,TEMP		;SELECTIVELY CLEAR TEMP
2283	013552	022767	100000	000372	CMP	#-77777-1&100000,TEMP		;COMPARE LITERAL TO TEMP
2284	013560	001401			BEQ	.+4		;TEST FOR EQUAL
2285	013562	000000			HLT			;BIC INSTRUCTION FAILED
2286	013564	000240			SCOPE			
2287	013566	012767	100000	000356	MOV	#100000,TEMP		;MOV 100000 TO TEMP
2288	013574	052767	077777	000350	BIS	#77777,TEMP		;SELECTIVE SET TEMP
2289	013602	022767	177777	000342	CMP	#100000!77777,TEMP		;COMPARE LITERAL TO TEMP
2290	013610	001401			BEQ	.+4		;TEST FOR EQUAL
2291	013612	000000			HLT			;BIS INSTRUCTION FAILED
2292	013614	000240			SCOPE			
2293	013616	012767	077777	000326	MOV	#77777,TEMP		;MOV 77777 TO TEMP
2294	013624	042767	100000	000320	BIC	#100000,TEMP		;SELECTIVELY CLEAR TEMP
2295	013632	022767	077777	000312	CMP	#-100000-1&77777,TEMP		;COMPARE LITERAL TO TEMP
2296	013640	001401			BEQ	.+4		;TEST FOR EQUAL
2297	013642	000000			HLT			;BIC INSTRUCTION FAILED
2298	013644	000240			SCOPE			
2299	013646	012767	077777	000276	MOV	#77777,TEMP		;MOV 77777 TO TEMP
2300	013654	052767	100000	000270	BIS	#100000,TEMP		;SELECTIVE SET TEMP
2301	013662	022767	177777	000262	CMP	#77777!100000,TEMP		;COMPARE LITERAL TO TEMP
2302	013670	001401			BEQ	.+4		;TEST FOR EQUAL
2303	013672	000000			HLT			;BIS INSTRUCTION FAILED
2304	013674	000240			SCOPE			
2305		000000			N=N+N			
2306		177777			M=M+M+1			
2307	013676	112767	000377	000246	MOVB	#377,TEMP		;MOV 377 TO TEMP
2308	013704	142767	052525	000240	BICB	#52525,TEMP		;SELECTIVELY CLEAR TEMP
2309	013712	122767	000252	000232	CMPB	#-52525-1&377,TEMP		;COMPARE LITERAL TO TEMP
2310	013720	001401			BEQ	.+4		;TEST FOR EQUAL
2311	013722	000000			HLT			;BIC INSTRUCTION FAILED
2312	013724	000240			SCOPE			
2313	013726	112767	000377	000216	MOVB	#377,TEMP		;MOV 377 TO TEMP
2314	013734	152767	052525	000210	BISB	#52525,TEMP		;SELECTIVE SET TEMP
2315	013742	122767	052777	000202	CMPB	#377!52525,TEMP		;COMPARE LITERAL TO TEMP
2316	013750	001401			BEQ	.+4		;TEST FOR EQUAL
2317	013752	000000			HLT			;BIS INSTRUCTION FAILED
2318	013754	000240			SCOPE			
2319	013756	112767	177400	000166	MOVB	#177400,TEMP		;MOV 177400 TO TEMP
2320	013764	142767	025252	000160	BICB	#25252,TEMP		;SELECTIVELY CLEAR TEMP
2321	013772	122767	152400	000152	CMPB	#-25252-1&177400,TEMP		;COMPARE LITERAL TO TEMP
2322	014000	001401			BEQ	.+4		;TEST FOR EQUAL
2323	014002	000000			HLT			;BIC INSTRUCTION FAILED
2324	014004	000240			SCOPE			
2325	014006	112767	177400	000136	MOVB	#177400,TEMP		;MOV 177400 TO TEMP
2326	014014	152767	025252	000130	BISB	#25252,TEMP		;SELECTIVE SET TEMP
2327	014022	122767	177652	000122	CMPB	#177400!25252,TEMP		;COMPARE LITERAL TO TEMP
2328	014030	001401			BEQ	.+4		;TEST FOR EQUAL
2329	014032	000000			HLT			;BIS INSTRUCTION FAILED
2330	014034	000240			SCOPE			
2331	014036	012767	000377	000106	MOV	#377,TEMP		;MOV 377 TO TEMP
2332	014044	042767	000707	000100	BIC	#0707,TEMP		;SELECTIVELY CLEAR TEMP

2333	014052	022767	000070	000072		CMP	#-0707-18377,TEMP	:COMPARE LITERAL TO TEMP
2334	014060	001401				BEQ	.+4	:TEST FOR EQUAL
2335	014062	000000				HLT		:BIC INSTRUCTION FAILED
2336	014064	000240				SCOPE		
2337	014066	012767	000377	000356		MOV	#377,TEMP	:MOV 377 TO TEMP
2338	014074	052767	000707	000050		BIS	#0707,TEMP	:SELECTIVE SET TEMP
2339	014102	022767	000777	000042		CMP	#377!0707,TEMP	:COMPARE LITERAL TO TEMP
2340	014110	001401				BEQ	.+4	:TEST FOR EQUAL
2341	014112	000000				HLT		:BIS INSTRUCTION FAILED
2342	014114	000240				SCOPE		
2343								
2344	014116	005267	000026			INC	LOOP	
2345	014122	100010				BPL	FIN	
2346	014124	012737	000207	177566		MOV	#207,2#177566	
2347	014132	105737	177564			TSTB	2#177564	
2348	014136	100375				BPL	.-4	
2349	014140	005067	000004			CLR	LOOP	
2350	014144	000137	000200			JMP	2#200	
2351	014150	000000			FIN:			
2352					LOOP:			
2353	014152	000000			TEMP:			
2354		000001					.END	

FIN 014144  
HLT = 000000

2345	2350*	319	323	327	331	335	339	343	347	351	358	362
266*	315	378	382	388	392	398	402	408	412	418	422	428
368	372	442	448	452	458	462	468	472	478	482	488	492
432	438	510	514	518	522	526	530	534	538	544	548	553
498	502	566	571	575	580	584	589	593	598	602	607	611
557	562	625	629	634	638	643	647	652	656	661	665	670
616	620	683	691	696	702	707	713	718	724	729	735	740
674	679	760	765	770	775	782	787	792	797	804	809	814
746	751	831	836	841	848	853	858	863	870	875	880	885
819	826	902	907	914	919	924	929	936	941	946	951	958
892	897	973	980	985	990	995	1002	1007	1012	1017	1024	1029
963	968	1046	1051	1056	1061	1068	1073	1078	1083	1090	1095	1100
1034	1039	1117	1124	1129	1134	1139	1144	1149	1154	1160	1165	1170
1105	1112	1185	1190	1196	1201	1206	1211	1216	1221	1226	1232	1237
1175	1180	1252	1257	1262	1268	1273	1278	1283	1288	1293	1298	1304
1242	1247	1319	1324	1329	1334	1341	1346	1351	1358	1364	1370	1376
1309	1314	1395	1401	1408	1414	1420	1426	1433	1439	1445	1451	1458
1383	1389	1476	1483	1489	1495	1501	1511	1517	1523	1529	1535	1541
1464	1470	1561	1567	1573	1579	1585	1591	1597	1603	1611	1617	1623
1547	1553	1641	1647	1653	1661	1667	1673	1679	1685	1691	1697	1703
1629	1635	1723	1729	1735	1741	1747	1753	1761	1767	1773	1779	1785
1711	1717	1803	1811	1817	1823	1829	1835	1841	1847	1853	1861	1867
1791	1797	1885	1891	1897	1903	1911	1917	1923	1929	1935	1941	1947
1873	1879	1967	1973	1979	1985	1991	1997	2003	2011	2017	2023	2029
1953	1961	2047	2053	2061	2067	2073	2079	2085	2091	2097	2103	2111
2035	2041	2129	2135	2141	2147	2153	2161	2167	2173	2179	2185	2191
2117	2123	2211	2217	2223	2229	2235	2241	2247	2253	2261	2267	2273
2197	2203	2291	2297	2303	2311	2317	2323	2329	2335	2341		
2279	2285	2351*										
2344*	2349*	359	364*	365	369	374*	375	379	384*	385	389	394*
354*	355	404*	405	409	414*	415	419	424*	425	429	434*	435
395	399	445	449	454*	455	459	464*	465	469	474*	475	479
439	444*	489	494*	495	499	504*	505	509	514*	515	519	524*
484*	485	788	793	799*	800	805	810	815	821*	822	827	832
778	783	844	849	854	859	865*	866	871	876	881	887*	888
837	843*	903	909*	910	915	920	925	931*	932	937	942	947
893	898	959	964	969	975*	976	981	986	991	997*	998	1003
953*	954	1019*	1020	1025	1030	1035	1041*	1042	1047	1052	1057	1063*
1008	1013	1074	1079	1085*	1086	1091	1096	1101	1107*	1119*	1155*	1191*
1064	1069	1299*	1335*	1506*	1507	1519	1531	1543	1556*	1557	1569	1581
1227*	1263*	1607	1619	1631	1643	1656*	1657	1669	1681	1693	1706*	1707
1593	1606*	1743	1756*	1757	1769	1781	1793	1806*	1807	1819	1831	1843
1719	1731	1869	1881	1893	1906*	1907	1919	1931	1943	1956*	1957	1969
1856*	1857	2006*	2007	2019	2031	2043	2056*	2057	2069	2081	2093	2106*
1981	1993	2131	2143	2156*	2157	2169	2181	2193	2206*	2207	2219	2231
2107	2119	2257	2269	2281	2293	2306*						
2243	2256*	355	359	363*	365	369	373*	375	379	383*	385	389
265	353*	399	403*	405	409	413*	415	419	423*	425	429	433*
393*	395	443*	445	449	453*	455	459	463*	465	469	473*	475
435	439	485	489	493*	495	499	503*	509	514*	515	519	524*
479	483*	558*	559	563	567*	568	572	576*	577	581	585*	586
550	554	599	599	603*	604	608	612*	613	617	621*	622	626
590	594*	635	639*	640	644	648*	649	653	657*	658	662	666*
630*	631	675*	676	680	684*	686*	688*	689	693*	694	697*	699*
667	671	705	708*	710*	711	715*	716	719*	721*	722	726*	727
700	704*											

LCOP 014150  
M = !77777

N = 000000

# K04

730#	732*	733	737*	738	741#	743*	744	748*	749	752#	754#	756
761	766	771	776#	778	783	788	793	798#	800	805	810	815
820#	822	827	832	837	842#	844	849	854	859	864#	866	871
876	881	886#	888	893	898	903	908#	910	915	920	925	930#
932	937	942	947	952#	954	959	964	969	974#	976	981	986
991	996#	998	1003	1008	1013	1018#	1020	1025	1030	1035	1040#	1042
1047	1052	1057	1062#	1064	1069	1074	1079	1084#	1086	1091	1096	1101
1106#	1121x	1122	1126*	1127	1131*	1132	1136*	1137	1141*	1142	1146*	1147
1151*	1152	1157*	1158	1162*	1163	1167*	1168	1172*	1173	1177*	1178	1182*
1183	1187*	1188	1193*	1194	1198*	1199	1203*	1204	1208*	1209	1213*	1214
1218*	1219	1223*	1224	1229*	1230	1234*	1235	1239*	1240	1244*	1245	1249*
1250	1254*	1255	1259*	1260	1265*	1266	1270*	1271	1275*	1276	1280*	1281
1285*	1286	1290*	1291	1295*	1296	1301*	1302	1306*	1307	1311*	1312	1316*
1317	1321*	1322	1326*	1327	1331*	1332	1353#	1354*	1355*	1356	1360*	1361*
1362	1366*	1367*	1368	1372*	1373*	1374	1378#	1379*	1380*	1381	1385*	1386*
1387	1391*	1392*	1393	1397*	1398*	1399	1403#	1404*	1405*	1406	1410*	1411*
1412	1416*	1417*	1418	1422*	1423*	1424	1428#	1429*	1430*	1431	1435*	1436*
1437	1441*	1442*	1443	1447*	1448*	1449	1453#	1454*	1455*	1456	1460*	1461*
1462	1466*	1467*	1468	1472*	1473*	1474	1478#	1479*	1480*	1481	1485*	1486*
1487	1491*	1492*	1493	1497*	1498*	1499	1503#	1505#	1507	1519	1531	1543
1555#	1557	1569	1581	1593	1605#	1607	1619	1631	1643	1655#	1657	1669
1681	1693	1705#	1707	1719	1731	1743	1755#	1757	1769	1781	1793	1805#
1807	1819	1831	1843	1855#	1857	1869	1881	1893	1905#	1907	1919	1931
1943	1955#	1957	1969	1981	1993	2005#	2007	2019	2031	2043	2055#	2057
2069	2081	2093	2105#	2107	2119	2131	2143	2155#	2157	2169	2181	2193
2205#	2207	2219	2231	2243	2255#	2257	2269	2281	2293	2305#		
265#												
264#	757*	758	762*	763	779*	780	784*	785	801*	802	806*	807
823#	824	828*	829	845*	846	850*	851	867*	868	872*	873	889*
890	894*	895	911*	912	916*	917	933*	934	938*	939	955*	956
960*	961	977*	978	982*	983	999*	1000	1004*	1005	1021*	1022	1026*
1027	1043*	1044	1048*	1049	1065*	1066	1070*	1071	1087*	1088	1092*	1093
1507*	1508*	1509	1513*	1514*	1515	1519*	1520*	1521	1525*	1526*	1527	1557*
1558*	1559	1563*	1564*	1565	1569*	1570*	1571	1575*	1576*	1577	1607*	1608*
1609	1613*	1614*	1615	1619*	1620*	1621	1625*	1626*	1627	1657*	1658*	1659
1663*	1664*	1665	1669*	1670*	1671	1675*	1676*	1677	1707*	1708*	1709	1713*
1714*	1715	1719*	1720*	1721	1725*	1726*	1727	1757*	1758*	1759	1763*	1764*
1765	1769*	1770*	1771	1775*	1776*	1777	1807*	1808*	1809	1813*	1814*	1815
1819*	1820*	1821	1825*	1826*	1827	1857*	1858*	1859	1863*	1864*	1865	1869*
1870*	1871	1875*	1876*	1877	1907*	1908*	1909	1913*	1914*	1915	1919*	1920*
1921	1925*	1926*	1927	1957*	1958*	1959	1963*	1964*	1965	1969*	1970*	1971
1975*	1976*	1977	2007*	2008*	2009	2013*	2014*	2015	2019*	2020*	2021	2025*
2026*	2027	2057*	2058*	2059	2063*	2064*	2065	2069*	2070*	2071	2075*	2076*
2077	2107*	2108*	2109	2113*	2114*	2115	2119*	2120*	2121	2125*	2126*	2127
2157*	2158*	2159	2163*	2164*	2165	2169*	2170*	2171	2175*	2176*	2177	2207*
2208*	2209	2213*	2214*	2215	2219*	2220*	2221	2225*	2226*	2227	2257*	2258*
2259	2263*	2264*	2265	2269*	2270*	2271	2275*	2276*	2277			
258#												
259#												
260#												
261#												
262#												
263#												
267#	312	316	320	324	328	332	336	340	344	348	355	359
365	369	375	379	385	389	395	399	405	409	415	419	425
429	435	439	445	449	455	459	465	469	475	479	485	489

RN =%000000  
 RJ =%000000

R1 =%000001  
 R2 =%000002  
 R3 =%000003  
 R4 =%000004  
 R5 =%000005  
 R6 =%000006  
 SCOPE = 000240

495	499	507	511	515	519	523	527	531	535	541	545	550
554	559	563	568	572	577	581	586	590	595	599	604	608
613	617	622	626	631	635	640	644	649	653	658	662	667
671	676	680	687	692	698	703	709	714	720	725	731	736
742	747	756	761	766	771	778	783	788	793	800	805	810
815	822	827	832	837	844	849	854	859	866	871	876	881
888	893	898	903	910	915	920	925	932	937	942	947	954
959	964	969	976	981	986	991	998	1003	1008	1013	1020	1025
1030	1035	1042	1047	1052	1057	1064	1069	1074	1079	1086	1091	1096
1101	1108	1113	1120	1125	1130	1135	1140	1145	1150	1156	1161	1166
1171	1176	1181	1186	1192	1197	1202	1207	1212	1217	1222	1228	1233
1238	1243	1248	1253	1258	1264	1269	1274	1279	1284	1289	1294	1300
1305	1310	1315	1320	1325	1330	1337	1342	1347	1359	1365	1371	1377
1384	1390	1396	1402	1409	1415	1421	1427	1434	1440	1446	1452	1459
1465	1471	1477	1484	1490	1496	1502	1512	1518	1524	1530	1536	1542
1548	1554	1562	1568	1574	1580	1586	1592	1598	1604	1612	1618	1624
1630	1636	1642	1648	1654	1662	1668	1674	1680	1686	1692	1698	1704
1712	1718	1724	1730	1736	1742	1748	1754	1762	1768	1774	1780	1786
1792	1798	1804	1812	1818	1824	1830	1836	1842	1848	1854	1862	1868
1874	1880	1886	1892	1898	1904	1912	1918	1924	1930	1936	1942	1948
1954	1962	1968	1974	1980	1986	1992	1998	2004	2012	2018	2024	2030
2036	2042	2048	2054	2062	2068	2074	2080	2086	2092	2098	2104	2112
2118	2124	2130	2136	2142	2148	2154	2162	2168	2174	2180	2186	2192
2198	2204	2212	2218	2224	2230	2236	2242	2248	2254	2262	2268	2274
2280	2286	2292	2298	2304	2312	2318	2324	2330	2336	2342		
767*	768	772*	773	789*	790	794*	795	811*	812	816*	817	833*
834	838*	839	855*	856	860*	861	877*	878	882*	883	899*	900
904*	905	921*	922	926*	927	943*	944	948*	949	965*	966	970*
971	987*	988	992*	993	1009*	1010	1014*	1015	1031*	1032	1036*	1037
1053*	1054	1058*	1059	1075*	1076	1080*	1081	1097*	1098	1102*	1103	1109*
1110	1114*	1115	1338*	1339	1343*	1344	1348*	1349	1531*	1532*	1533	1537*
1538*	1539	1543*	1544*	1545	1549*	1550*	1551	1581*	1582*	1583	1587*	1588*
1589	1593*	1594*	1595	1599*	1600*	1601	1631*	1632*	1633	1637*	1638*	1639
1643*	1644*	1645	1649*	1650*	1651	1681*	1682*	1683	1687*	1688*	1689	1693*
1694*	1695	1699*	1700*	1701	1731*	1732*	1733	1737*	1738*	1739	1743*	1744*
1745	1749*	1750*	1751	1781*	1782*	1783	1787*	1788*	1789	1793*	1794*	1795
1799*	1800*	1801	1831*	1832*	1833	1837*	1838*	1839	1843*	1844*	1845	1849*
1850*	1851	1881*	1882*	1883	1887*	1888*	1889	1893*	1894*	1895	1899*	1900*
1901	1931*	1932*	1933	1937*	1938*	1939	1943*	1944*	1945	1949*	1950*	1951
1981*	1982*	1983	1987*	1988*	1989	1993*	1994*	1995	1999*	2000*	2001	2031*
2032*	2033	2037*	2038*	2039	2043*	2044*	2045	2049*	2050*	2051	2081*	2082*
2083	2087*	2088*	2089	2093*	2094*	2095	2099*	2100*	2101	2131*	2132*	2133
2137*	2138*	2139	2143*	2144*	2145	2149*	2150*	2151	2181*	2182*	2183	2187*
2188*	2189	2193*	2194*	2195	2199*	2200*	2201	2231*	2232*	2233	2237*	2238*
2239	2243*	2244*	2245	2249*	2250*	2251	2281*	2282*	2283	2287*	2288*	2289
2293*	2294*	2295	2299*	2300*	2301	2307*	2308*	2309	2313*	2314*	2315	2319*
2320*	2321	2325*	2326*	2327	2331*	2332*	2333	2337*	2338*	2339	2353*	
269*	270	272	274	276	278	280	282	284	286	288	290	292
294	296	298	300	302*	314	318	322	326	330	334	338	342
346	350	357	361	367	371	377	381	387	391	397	401	407
411	417	421	427	431	437	441	447	451	457	461	467	471
477	481	487	491	497	501	509	513	517	521	525	529	533
537	543	547	552	556	561	565	570	574	579	583	588	592
597	601	606	610	615	619	624	628	633	637	642	646	651
655	660	664	669	673	678	682	690	695	701	706	712	717
723	728	734	739	745	750	759	764	769	774	781	786	791

TEMP 014152

= 014154









SEC	314	318	322	326	330	334	338	342	346	350	357	361	367	371	377
	381	387	391	397	401	407	411	417	421	427	431	437	441	447	451
	457	461	467	471	477	481	487	491	497	501	690	695	701	706	712
	717	723	728	734	739	745	750	755	764	769	774	781	786	791	796
	803	808	813	818	825	830	835	840	847	852	857	862	869	874	879
	884	891	896	901	906	913	918	923	928	935	940	945	950	957	962
	967	972	979	984	989	994	1001	1006	1011	1016	1023	1028	1033	1038	1045
	1050	1055	1060	1067	1072	1077	1082	1089	1094	1099	1104	1111	1116	1357	1363
	1369	1375	1382	1388	1394	1400	1407	1413	1419	1425	1432	1438	1444	1450	1457
	1463	1469	1475	1482	1488	1494	1500	1510	1516	1522	1528	1534	1540	1546	1552
	1560	1566	1572	1578	1584	1590	1596	1602	1610	1616	1622	1628	1634	1640	1646
	1652	1660	1666	1672	1678	1684	1690	1696	1702	1710	1716	1722	1728	1734	1740
	1746	1752	1760	1766	1772	1778	1784	1790	1796	1802	1810	1816	1822	1828	1834
	1840	1845	1852	1860	1866	1872	1878	1884	1890	1896	1902	1910	1916	1922	1928
	1934	1940	1946	1952	1960	1966	1972	1978	1984	1990	1996	2002	2010	2016	2022
	2028	2034	2040	2046	2052	2060	2066	2072	2078	2084	2090	2096	2102	2110	2116
	2122	2128	2134	2140	2146	2152	2160	2166	2172	2178	2184	2190	2196	2202	2210
	2216	2222	2228	2234	2240	2246	2252	2260	2266	2272	2278	2284	2290	2296	2302
	2310	2316	2322	2328	2334	2340									
BIC	1355	1367	1380	1392	1405	1417	1430	1442	1455	1467	1480	1492	1508	1520	1532
	1544	1558	1570	1582	1594	1606	1620	1632	1644	1658	1670	1682	1694	1708	1720
	1732	1744	1758	1770	1782	1794	1808	1820	1832	1844	1858	1870	1882	1894	1908
	1920	1932	1944	1958	1970	1982	1994	2008	2020	2032	2044	2058	2070	2082	2094
	2108	2120	2132	2144	2158	2170	2182	2194	2208	2220	2232	2244	2258	2270	2282
	2294	2332													
BICB	2308	2320													
BIC	1361	1373	1386	1398	1411	1423	1436	1448	1461	1473	1486	1498	1514	1526	1538
	1550	1564	1576	1588	1600	1614	1626	1638	1650	1664	1676	1688	1700	1714	1726
	1738	1750	1764	1776	1788	1800	1814	1826	1838	1850	1864	1876	1888	1900	1914
	1926	1938	1950	1964	1976	1988	2000	2014	2026	2038	2050	2064	2076	2088	2100
	2114	2126	2138	2150	2164	2176	2188	2200	2214	2226	2238	2250	2264	2276	2288
	2300	2338													
BICB	2314	2326													
BIC	313	317	321	325	329	356	360	365	370	376	380	386	390	396	400
	406	410	416	420	426	430	436	440	446	450	456	460	466	470	476
	480	486	490	496	500	508	512	516	520	524	542	546	551	555	560
	564	569	573	578	582	587	591	596	600	605	609	614	618	623	627
	633	636	641	645	650	654	659	663	668	672	677	681	689	694	700
	705	711	716	722	727	733	738	744	749	758	763	768	773	780	785
	790	795	802	807	812	817	824	829	834	839	846	851	856	861	868
	873	878	883	890	895	900	905	912	917	922	927	934	939	944	949
	956	961	966	971	978	983	988	993	1000	1005	1010	1015	1022	1027	1032
	1037	1044	1049	1054	1059	1066	1071	1076	1081	1088	1093	1098	1103	1122	1127
	1132	1137	1142	1158	1163	1168	1173	1178	1194	1199	1204	1209	1214	1230	1235
	1240	1245	1250	1266	1271	1276	1281	1286	1302	1307	1312	1317	1322	1339	1345
BICB	333	337	341	345	349	528	532	536	1110	1115	1147	1152	1183	1188	1219
BIC	1224	1255	1260	1291	1296	1327	1332	1344	1349						
	509	513	517	521	525	529	533	537	543	547	552	556	561	565	570
	574	579	583	588	592	597	601	606	610	615	619	624	628	633	637
	642	646	651	655	660	664	669	673	678	682	1123	1128	1133	1138	1143
	1148	1153	1159	1164	1169	1174	1179	1184	1189	1195	1200	1205	1210	1215	1220
	1225	1231	1236	1241	1246	1251	1256	1261	1267	1272	1277	1282	1287	1292	1297
	1303	1308	1313	1318	1323	1328	1333	1340	1345	1350					
BICB	2345	2348													
BIC	1356	1362	1368	1374	1381	1387	1393	1399	1406	1412	1418	1424	1431	1437	1443

	1449	1456	1462	1468	1474	1481	1487	1493	1499	1509	1515	1521	1527	1533	1539
	1545	1551	1559	1565	1571	1577	1583	1599	1595	1601	1609	1615	1621	1627	1633
	1639	1645	1651	1659	1665	1671	1677	1683	1689	1695	1701	1709	1715	1721	1727
	1733	1739	1745	1751	1759	1765	1771	1777	1783	1789	1795	1801	1809	1815	1821
	1827	1833	1839	1845	1851	1859	1865	1871	1877	1883	1889	1895	1901	1909	1915
	1921	1927	1933	1939	1945	1951	1959	1965	1971	1977	1983	1989	1995	2001	2009
	2015	2021	2027	2033	2039	2045	2051	2059	2065	2071	2077	2083	2089	2095	2101
	2109	2115	2121	2127	2133	2139	2145	2151	2159	2165	2171	2177	2183	2189	2195
	2201	2209	2215	2221	2227	2233	2239	2245	2251	2259	2265	2271	2277	2283	2289
	2295	2301	2307	2313	2319	2325	2331	2337	2343	2349	2355	2361	2367	2373	2379
CMPB	2385	2391	2397	2403	2409	2415	2421	2427	2433	2439	2445	2451	2457	2463	2469
HALT	2475	2481	2487	2493	2499	2505	2511	2517	2523	2529	2535	2541	2547	2553	2559
TNC	2565	2571	2577	2583	2589	2595	2601	2607	2613	2619	2625	2631	2637	2643	2649
MOV	2655	2661	2667	2673	2679	2685	2691	2697	2703	2709	2715	2721	2727	2733	2739
	688	693	699	704	710	715	721	726	732	737	743	748	757	762	767
	772	779	784	799	794	801	806	811	816	823	828	833	838	845	850
	855	860	867	872	877	882	889	894	899	904	911	916	921	926	933
	938	943	948	955	960	965	970	977	982	987	992	999	1004	1009	1014
	1021	1026	1031	1036	1043	1048	1053	1058	1065	1070	1075	1080	1087	1092	1097
	1102	1109	1114	1121	1126	1131	1136	1141	1146	1151	1157	1162	1167	1172	1177
	1182	1187	1193	1198	1203	1208	1213	1218	1223	1229	1234	1239	1244	1249	1254
	1259	1265	1270	1275	1280	1285	1290	1295	1301	1306	1311	1316	1321	1326	1331
	1338	1343	1348	1354	1360	1366	1372	1379	1385	1391	1397	1404	1410	1416	1422
	1429	1435	1441	1447	1454	1460	1466	1472	1479	1485	1491	1497	1507	1513	1519
	1525	1531	1537	1543	1549	1557	1563	1569	1575	1581	1587	1593	1599	1607	1613
	1619	1625	1631	1637	1643	1649	1657	1663	1669	1675	1681	1687	1693	1699	1707
	1713	1719	1725	1731	1737	1743	1749	1757	1763	1769	1775	1781	1787	1793	1799
	1807	1813	1819	1825	1831	1837	1843	1849	1857	1863	1869	1875	1881	1887	1893
	1899	1907	1913	1919	1925	1931	1937	1943	1949	1957	1963	1969	1975	1981	1987
	1993	1999	2007	2013	2019	2025	2031	2037	2043	2049	2057	2063	2069	2075	2081
	2087	2093	2099	2107	2113	2119	2125	2131	2137	2143	2149	2157	2163	2169	2175
	2181	2187	2193	2199	2207	2213	2219	2225	2231	2237	2243	2249	2257	2263	2269
	2275	2281	2287	2293	2299	2305	2311	2317	2323	2329	2335	2341	2347	2353	2359
MC.B	2365	2371	2377	2383	2389	2395	2401	2407	2413	2419	2425	2431	2437	2443	2449
TSTB	2455	2461	2467	2473	2479	2485	2491	2497	2503	2509	2515	2521	2527	2533	2539
.ENABL	1														
.ENC	2354														
.LIST	1														
.MACR	304	305	306	307	308	309	310								
.MACRO	1														
.MLIST	1														
.REM	1														
.REPT	270	355	541	687	756	1120	1354	1507							

ERRORS DETECTED: 0  
DEFAULT GLOBALS GENERATED: 0

\* DOIA.SEQ/SOL/CRF/PAGNUM/NL:TOC=SYSMAC.CO,DOIA.P11  
RUN-TIME: 30 40 4 SECONDS  
RUN-TIME RATIO: 378/75=5.0  
CORE USED: 32K (63 PAGES)

