

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	1590-04
Description	SuperSCRIPSIT
Model	Model III
Stock No.	26-1590 01.02.02
Date	February 17, 1984
Page 1 of	1

Problem

Adverse operating conditions such as a power outage or an improper exit from the program can cause a screen to "garbage" out and the program to lock up. Patches are shown below to reduce the chances of this situation occurring.

* * THE FOLLOWING PATCHES ARE REQUIRED! * *

Solution

Apply the following patches.

```
PATCH SCR16/CTL (ADD=8DE8,FIND=EDB0DD7E00,CHG=CDB07C0000)
PATCH SCRIPSIT/CMD (ADD=7CB0,FIND=0000000000,CHG=E5210000CD)
PATCH SCRIPSIT/CMD (ADD=7CB5,FIND=0000000000,CHG=C165E12802)
PATCH SCRIPSIT/CMD (ADD=7CBA,FIND=0000000000,CHG=EDB0DD7E00)
PATCH SCRIPSIT/CMD (ADD=7CBF,FIND=00,CHG=C9)
```

Apply the following patch to change the Version Number from 01.02.02 to 01.02.03. Please enter the new version number in your Version Log.

```
PATCH SCR17/CTL (ADD=8EC7,FIND=32,CHG=33)
```