

# CUSTOMER SERVICE BULLETIN

## Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	491Ø-16
Description	TRSDOS
Model	Model II
Stock No.	26-491Ø Version 2.Øa
Date	Dec. 16, 1981
Page 1 of	1

### Problem

These patches are to change the operation of the Terminal program from serial channel A to serial channel B on a permanent basis. Do not apply these patches unless you have a special situation which requires the use of the terminal program channel B only. Please note that you should not try to use a Serial Printer (which also uses Channel B) once these patches have been applied. If you attempt to do so, bytes will be intermixed on channel B.

### Solution

PATCH TERMINAL A=343C F=3E61 C=3E63  
PATCH TERMINAL A=3488 F=3E6Ø C=3E62  
PATCH TERMINAL A=352C F=3E64 C=3E65  
PATCH TERMINAL A=3535 F=3E64 C=3E65  
PATCH TERMINAL A=353F F=3E64 C=3E65  
PATCH TERMINAL A=3549 F=3E61 C=3E63  
PATCH TERMINAL A=3583 F=3E6Ø C=3E62  
PATCH TERMINAL A=36A9 F=3E6Ø C=3E62  
PATCH TERMINAL A=36D6 F=3E6Ø C=3E62