

# CUSTOMER SERVICE BULLETIN

## Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No. 1559-4  
Description Mfg Inventory Control  
Model Model I  
Stock No. 26-1559 Version 1.2  
Date May 28, 1980  
Page 1 of 1

### Problem

The system may reboot at times when doing an inactive raw material list. This shouldn't happen, but the situation can be avoided.

### Solution

The problem is corrected by following the steps listed below.

1. Backup the diskette(s) and make the changes on the Backup copy of the program.
2. In BASIC load the program by typing LOAD"REPORT2".
3. Make the following corrections:

CHANGES (Retype the line or refer to the Edit section of the owners manual)

Old Line: 4110 FORZ=1TONF:HL=USR0(VARPTR(FG(PT))):IFHL>0THENP=0

New Line: 4110 FORZ=1TONF:GOSUB11010:HL=USR0(VARPTR(FG(PT))):IFHL>0THENP=0

4. Type SAVE"REPORT2" to save the changes in the program.
5. At TRSDOS Ready, make a backup copy of the corrected diskette.