

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

| | |
|--------------|----------------------|
| Bulletin No. | 4530-4 |
| Description | Scripsit |
| Model | Model II |
| Stock No. | 26-4530 Version 1.0a |
| Date | February 19, 1981 |
| Page 1 of | 1 |

Problem

When an alignment tab is terminated by an ENTER instead of a period, Scripsit was not accepting the ENTER as a valid terminator. The following patches fix this problem.

Solution

1. Reset the system and insert a Scripsit diskette.
2. Answer the Date Prompt.
3. Press HOLD.
4. Answer the Time Prompt.
5. Enter the following patches at TRSDOS READY.

```
PATCH SCRIPSIT A=9CD8 F=FD8E16 C=C320DC
```

```
PATCH SCRIPSIT A=DC20 F=0000000000000000 C=FD8E16CAEB9CFE0D
```

```
PATCH SCRIPSIT A=DC29 F=0000000000000000 C=CAEB9CC3DD9C
```

6. Type STARTUP and press ENTER. Scripsit will load.
7. Make a backup of your Scripsit diskette.