

# CUSTOMER SERVICE BULLETIN

## Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No. 4910-5  
Description TRSDOS Terminal  
Model Model II  
Stock No. 26-4910 Version 1.2  
Date July 16, 1980  
Page 1 of 1

### Problem

In the Terminal program, some host systems use a "Marking" parity during ASYNC transmission. Current communications software would detect this as a parity error. Normal programming to handle this is done by ignoring parity errors in the applications program. The following patches will allow TERMINAL program to ignore the error conditions of parity, framing, or overrun. Caution should be used, however, since using any of these patches will cause true errors to go through, unreported.

### Solution

Patch to ignore PARITY errors:

PATCH TERMINAL A=33D7 F=CB67 C=1804

Patch to ignore OVERRUN errors:

PATCH TERMINAL A=33DD F=CB6F C=1804

Patch to ignore FRAMING errors:

PATCH TERMINAL A=33E3 F=CB77 C=1814