

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	6105-06
Description	TRSDOS 16
Model	Model II/16
Stock No.	26-6105 Version 4.1
Date	July 13, 1982
Page 1 of	1

Problem

The patches listed below will permanently change HOST to function from channel B instead of channel A. These patches should not be applied unless one has a special situation which requires the use of the HOST function on channel B. Please note that a serial printer (which uses channel B) may not be used concurrently with HOST once these patches have been applied.

* * THESE PATCHES ARE OPTIONAL! * *

Solution

```
PATCH SYSTEM/SYS R=110 B=204 F=606164 C=626365
PATCH SYSTEM/SYS R=64 B=164 F=41 C=42
PATCH SYSTEM/SYS R=64 B=173 F=CB5E28E1CB9E0660 C=CB5628E1CB960662
PATCH SYSTEM/SYS R=64 B=191 F=64 C=65
PATCH SYSTEM/SYS R=64 B=198 F=42 C=41
PATCH SYSTEM/SYS R=64 B=201 F=CB5628C5CB960662 C=CB5E28C5CB9E0660
PATCH SYSTEM/SYS R=64 B=219 F=65 C=64
```